Amended Proposed Revised

proposed revisions to the Access

Arrangement for the Western Power Network

ELECTRICITY NETWORKS CORPORATION ("WESTERN POWER")

ABN 18 540 492 861

2 October 2017

14 June 2018 16 November 2018



363 Wellington Street Perth 6000 GPO Box L921 Perth WA 6842 e enquiry@westernpower.com.au westernpower.com.au



t 13 10 87 f (08) 9225 2660 TTY 1800 13 13 51 TIS 13 14 50

Electricity Networks Corporation ABN: 18 540 492 861

Contents

1 Introduction		tion	6
	1.1	Purpose of this document	6
	1.2	Definitions and interpretation	6
	1.3	Proposed access arrangement revisions commencement date	6
	1.4	Revisions submission date and target revisions commencement date	7
	1.5	Composition of this access arrangement	7
	1.6	Relationship to technical rules and access arrangement information	7
2	Referen	ce services	8
	2.1	Purpose	8
	2.2	Reference services	8
	2.3	Payment by users	12
3	Excluded	d services	13
	3.1	Purpose	13
	3.2	Excluded services	13
4	Service s	standard benchmarks	14
	4.1	Purpose	14
	4.2	Service standard benchmarks for distribution reference services	14
	4.3	Service standard benchmarks for transmission reference services	19
	4.4	Service standard benchmarks for street lighting reference services	25
	4.5	Service standard benchmark for supply abolishment reference service	26
	4.6	Service standard benchmarks for remote de-energise and remote re-energise	
		reference services	28
	4.7	Exclusions	31
5	Price co	ntrol	32
	5.1	Overview of price control	32
	5.2	Capital base value	33
	5.3	Depreciation	35
	5.4	Weighted average cost of capital	37
	5.5	Deferred revenue from the second and third access arrangement period	40
	5.6	Transmission system price control – period of application	43
	5.7	Transmission system price control for revenue target services – years ending 30 Ju	ne
		2018 and 30 June 2019	43
	5.8	Transmission system price control for revenue target services – years ending 30 Ju	ne
		2020, 30 June 2021 and 30 June 2022	45
	5.9	Distribution system price control – period of application	46
	5.10	Distribution system price control for revenue target services – years ending 30 Jun	е
		2018 and 30 June 2019	47



	5.11	Distribution system price control for revenue target services – years ending 30) June
		2020, 30 June 2021 and 30 June 2022	49
6	Pricing I	methods, price lists and price information	52
	6.1	Purpose	52
	6.2	Network pricing objectives	52
	6.3	Overview of pricing methods	
	6.4	Price list and price list information	53
	6.5	Pricing methods	55
	6.6	Policy on prudent discounting	64
	6.7	Policy on discounts for distributed generation	64
7	Adjustn	nents to target revenue in the next access arrangement period	66
	7.1	Adjusting target revenue for unforeseen events	66
	7.2	Adjusting target revenue for technical rule changes	67
	7.3	Investment adjustment mechanism	67
	7.4	Gain sharing mechanism and efficiency and innovation benchmarks	68
	7.5	Service standards adjustment mechanism	77
	7.6	D factor	82
	7.7	Deferred revenue	83
8	Trigger	events	85
9	Supplen	nentary matters	86
	9.1	General	86
	9.2	Line losses	86
	9.3	Metering	86
APPE	NDICES	88	
Арре	endix A.	Electricity transfer access contract	89
Арре	endix B.	Applications and queuing policy	90
Арре	endix C.	Contributions policy	91
	C.1	Contributions policy	91
	C.2	Distribution low voltage connection scheme methodology	91
Арре	endix D.	Transfer and relocation policy	92
Арре	endix E.	Reference services	93
Appe	endix F.	Reference tariffs	94
	F.1	2017/18 price list	94
	F.2	2017/18 price list information	94
	F.3	2018/19 price list	94
	F.4	2018/19 price list information	94
	F.5	2019/20 price list	94
	F.6	2019/20 price list information	94



List of Tables

List of Tables		Page no.
Table 1:	Reference services at exit points	8
Table 2:	Reference services at entry points	9
Table 3:	Reference services at entry points	9
Table 3:	Reference services at connection points (ancillary)	9
Table 4:	Standard metering services	10
Table 5:	Application of SAIDI	13
Table 7:	SAIDI service standard benchmarks for reference services A1 to A8, A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7	15
Table 8:	Application of SAIFI	15
Table 9:	SAIFI service standard benchmarks for reference services A1 to A8, A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7	16
Table 10:	Application of call centre performance	17
Table 11:	Call centre service standard benchmarks for reference services A1 to A8, A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7	18
Table 12:	Application of circuit availability	18
Table 13:	Circuit availability service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7	19
Table 14:	Application of loss of supply event frequency	19
Table 15:	Loss of supply event frequency service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7	20
Table 16:	Application of average outage duration	21
Table 17:	Average outage duration service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7	21
Table 18:	Application of street lighting repair time	22
Table 6:	Street lighting repair time service standard benchmark for reference service A9	23
Table 7:	Application of supply abolishment (whole current meter) response time	23
Table 21:	Supply abolishment (whole current meter) response time service standard benchmark for reference service D1	24
Table 8:	Application of remote de-energise response time	25
Table 23:	Remote de-energise response time service standard benchmark for reference service D8	26
Table 9:	Application of remote re-energise response time	26
Table 10:	Remote re-energise response time service standard benchmark for reference service D9	27



List of Tables	Page no.
Table 11: Derivation of Transmission Initial Capital Base (net) (\$ million real as at 30 June 2017)	30
Table 12: Derivation of Distribution Initial Capital Base (net) (\$ million real as at 30 June 2017)	30
Table 13: Transmission asset groupings and economic lives for depreciation purposes	31
Table 29: Distribution asset groupings and economic lives for depreciation purposes	31
Table 14: Distribution accelerated depreciation by asset class (\$ million real as at 30 June 2017)	32
Table 15: Derivation of transmission system deferred revenue (\$ million real as at 30 June 2017)	35
Table 32: Derivation of distribution system deferred revenue (\$ million real as at 30 June 2017)	36
Table 33: Amount to be added to the target revenue due to the recovery of deferred revenue (\$ million real as at 30 June 2017)	36
Table 34:Transmission revenue target service revenues to be used for calculating TRt (\$ million real as at 30 June 2017)	38
Table 16: Distribution revenue cap service revenues to be used for calculating DRt (\$ million real as at 30 June 2017)	39
Table 36: Pricing years for this access arrangement period	43
Table 37: Customer numbers and energy volumes	44
Table 38: Xt	47
Table 39: Efficiency and innovation benchmarks (\$M real as at 30 June 2017)	52
Table 40: Distribution system forecast network growth escalation assumptions	55
Table 41: Transmission system forecast network growth escalation assumptions	55
Table 42: Indirect cost forecast growth escalation assumptions	56
Table 43: SAIDI SSAM targets and incentive rates (\$ real as at 30 June 2017)	58
Table 44: SAIFI SSAM targets and incentive rates (\$ real as at 30 June 2017)	58
Table 45: Call centre performance SSAM target and incentive rate (\$ real as at 30 June 2017)	58
Table 46: Circuit availability SSAM target and incentive rate (\$ real as at 30 June 2017)	59
Table 47: Loss of supply event frequency SSAM target and incentive rate (\$ real as at 30 June 2017)	59
Table 48: Average outage duration SSAM target and incentive rate (\$ real as at 30 June 2017)	59



1 Introduction

1.1 Purpose of this document

- 1.1.1 These <u>amended revised amended</u> proposed revisions are lodged by Western Power on <u>2</u> October 20122017 for<u>14 June 2018-16 November 2018 for</u> review and approval by the Authority in accordance with the processes and criteria set out in the *Electricity Networks Access Code 2004*, herein referred to as the <u>"Code"</u>. Henceforth this document is referred to as the "access arrangement".
- 1.1.2 This access arrangement is an arrangement for access to the Western Power Network from the date specified in section 1.3.1 of this access arrangement. The Western Power Network is a covered network under the Code.

1.2 Definitions and interpretation

- 1.2.1 In sections 1 to 9 of this *access arrangement*, where a word or phrase is italicised it has the definition given to that word or phrase as described in this *access arrangement* or section 1.3 of the *Code*, unless the context requires otherwise.
- **1.2.2** In each of the appendices to this *access arrangement*, a separate glossary of terms is provided where appropriate, and the definitions contained in those separate glossaries apply to the relevant appendix, unless the context requires otherwise.

1.2.3 In this access arrangement:

<u>"AMI Meter" has the meaning given to it in the model service level agreement most</u> recently approved by the Authority under the Electricity Industry (Metering Code) 2012.

"bi-directional service" means a covered service provided by Western Power at a connection point under which the user may transfer electricity into and out of the Western Power Network at the connection point.

"MSLA" means the model service level agreement approved by the Authority under the Metering Code (which as at the AA4 effective date is the version dated March 2006).

1.3 Proposed access arrangement revisions commencement date

 1.3.1 This access arrangement (as <u>amendedrevised</u>) is effective from 1 <u>July 2019</u> <u>JulyNovemberFebruary 2013</u> <u>2018</u> or a later date in accordance with section 4.26 of the *Code*.



1.4 Revisions submission date and target revisions commencement date

- 1.4.1 Pursuant to section 5.31(a) of the *Code*, the *revisions submission date* for this *access* arrangement is <u>31 December 2016.1 March26 February 2021.</u>
- 1.4.2 Pursuant to section 5.31(b) of the *Code*, the target *revisions commencement date* for this *access arrangement* is 1 July 20172022.

1.5 Composition of this access arrangement

- 1.5.1 This *access arrangement* comprises this document together with:
 - a) the *Standard Access Contract*, termed the Electricity Transfer Access Contract attached at Appendix A;
 - b) the Applications and Queuing Policy attached at Appendix B;
 - c)—the Contributions Policy attached at Appendix C.1;
 - d)c) the distribution headworks methodology attached at Appendix 0;
 - e)d) the dDistribution Low Voltage Connection headworks sScheme mMethodology attached at Appendix A.1; C.2;
 - f)e) the Transfer and Relocation Policy attached at Appendix D;
 - g)f) the details of the reference services offered by Western Power attached at Appendix E;
 - h)g) the price <u>listlists</u> attached at Appendix F.1F, which <u>isare</u> a schedule of reference tariffs in effect for this access arrangement; and
 - i)h) the price list information attached at Appendix ,Appendix F, which explains how Western Power derived the elements of the proposed price <u>listlists</u>; and demonstrates that the price <u>list complies</u> with the access arrangement.

1.6 Relationship to technical rules and access arrangement information

- 1.6.1 The *technical rules* do not form part of this *access arrangement*, although the *technical rules* are relevant in determining Western Power's *target revenue*.
- 1.6.2 Western Power's <u>amended proposed access arrangement information is submitted</u> ondated <u>16 November 2018 201714 June 2018 is submitted</u> alongside this access arrangement in accordance with section 4.4 of the *Code*. The <u>amended amended</u> proposed access arrangement information is to be read in conjunction with the revised access arrangement information that was submitted on 14 June 20182 October 2017 and the access arrangement information that was submitted on 2 October 2017. The amended proposed access arrangement information, amended proposed access arrangement information and the <u>revised</u>-access arrangement information do not form part of this access arrangement.



EDM 44531823 Page 7

2 Reference services

2.1 Purpose

2.1.1 Pursuant to sections 5.1(a) and 5.2 of the *Code*, this section of the *access arrangement* describes the *reference services* offered by Western Power.

2.2 Reference services

- 2.2.1 In this access arrangement:
- 2.2.2 **"bi directional service**" means a covered service provided by Western Power at a connection point under which the user may transfer electricity into and out of the Western Power Network at the connection point.

<u>"AMI Meter" has the meaning given to it in the model service level agreement most</u> recently approved by the Authority under the Electricity Industry (Metering Code) 2012.

<u>"AMI metering installation" means a metering installation with an AMI Meter (other than a compliance meter).</u>

<u>"compliance meter"</u> means an AMI Meter that has been installed under Schedule 3,
 <u>clause 3.2 (Meter Upgrade) of the model service level agreement most recently approved</u>
 <u>by the Authority under the Electricity Industry (Metering Code) 2012.</u>

<u>"compliance metering installation" means a metering installation with a compliance</u> meter.

<u>"metering installation" has the meaning given to it in the Electricity Industry (Metering</u> <u>Code) 2012.</u>

- 2.2.32.2.1 Reference services are provided to users that meet and continue to meet the eligibility criteria applicable to the reference service provided, on the terms and conditions of the Electricity Transfer Access Contract, at the related service standard benchmarks and at the related reference tariff.
- 2.2.42.2.2 Western Power specifies 147 reference services at exit points and bi directional points:

Table 2.11: Reference services at exit points and bi-directional points

Table 17: Reference services at exit points

Reference service	Short name
Anytime Energy (Residential) Exit Service	A1



Reference service	Short name
Anytime Energy (Business) Exit Service	A2
Time of Use Energy (Residential) Exit Service	A3
Time of Use Energy (Business) Exit Service	A4
High Voltage Metered Demand Exit Exit-Service	A5
Low Voltage Metered Demand Exit Exit Service	A6
High Voltage Contract Maximum Demand Exit Exit Service	Α7
Low Voltage Contract Maximum Demand Exit Exit-Service	A8
Streetlighting Exit Service (including streetlight maintenance)	A9
Un <u>m</u> -Metered Supplies Exit Service	A10
Transmission Exit Service	A11
3 Part Time of Use Energy (Residential) Exit Service	<u>A12</u>
3 Part Time of Use Energy (Business) Exit Service	<u>A13</u>
3 Part Time of Use Demand (Residential) Exit Service	<u>A14</u>
3 Part Time of Use Demand (Business) Exit Service	<u>A15</u>
Multi Part Time of Use Energy (Residential) Exit Service	<u>A16</u>
Multi Part Time of Use Energy (Business) Exit Service	<u>A17</u>



2.2.5 Western Power specifies twothree reference services at entry points: Table 2.22: Reference services at entry points

Table 18: Reference services at entry points

Reference service	Short name
Distribution Entry Service	B1
Transmission Entry Service	B2
Entry Service Facilitating a Distributed Generation or Other Non-Network Solution	<u>B3</u>

<u>2.2.3</u> Western Power specifies four <u>eight15</u> bi-directional services as reference services at connection points:

Table 2.33: Reference services at Bbi directional points services that are reference services

Table 19: Reference services at bi-directional points

Reference service name	Short name
Anytime Energy (Residential) Bi-Ddirectional Service	C1
Anytime Energy (Business) Bi-Ddirectional Service	C2
Time Of Use Energy (Residential) Bi-Ddirectional Service	C3
Time Of Use Energy (Business) Bi-Ddirectional Service	C4
High Voltage Metered Demand Bi-directional Service	<u>C5</u>
Low Voltage Metered Demand Bi-directional Service	<u>C6</u>
High Voltage Contract Maximum Demand Bi-directional Service	<u>C7</u>
Low Voltage Contract Maximum Demand Bi-directional Service C8	
3 Part Time of Use Energy (Residential) Bi-directional Service	<u>C9</u>
3 Part Time of Use Energy (Business) Bi-directional Service	<u>C10</u>
3 Part Time of Use Demand (Residential) Bi-directional Service	<u>C11</u>
3 Part Time of Use Demand (Business) Bi-directional Service	<u>C12</u>
Multi Part Time of Use Demand (Residential) Bi-directional Service C13	
Multi Part Time of Use Demand (Business) Bi-directional Service C14	
Bi-directional Service Facilitating a Distributed Generation or Other Non-Network Solution	<u>C15</u>

Western Power specifies fourtwo services at an exit point or a bi-directional point with an AMI meter or an interval metering installation or a compliance metering installation as reference services.

<u>Table 4: Reference Services at an exit point or a bi-directional point with an AMI meter or</u> an interval meterwith an AMI metering installation or a compliance metering installation



<u>Reference service name</u>	<u>Short name</u>
<u>—————————————————————————————————————</u>	<u>—D1</u>
Time of Use Energy (Business) AMI Service3 Part Time of Use Energy (Business) Service	<u>—D2</u>
Time of Use Demand (Residential) AMI Service	<u></u> D3
Time of Use Demand (Business) AMI Service	<u>——</u> <u>D4</u>

2.2.6

2.2.4 Western Power specifies nine *services* at a *connection point* as a *reference service* (ancillary).

Table 2.4: Reference services at connection points (ancillary)

Table 20: Reference services at connection points (ancillary)

Reference service name	Short name
Supply Abolishment (whole current metering) Service	<u>D1</u>
Capacity Allocation Swap (Nominator) (Business) Service	<u>D2</u>
Capacity Allocation Swap (Nominee) (Business) Service	<u>D3</u>
Capacity Allocation Same Connection Point (Nominator) (Business) Service	<u>D4</u>
Capacity Allocation Same Connection Point (Nominee) (Business) Service	<u>D5</u>
Remote Direct Load Control Service	<u>D6</u>
Remote Load Limitation Service	<u>D7</u>
Remote De-energise Service	<u>D8</u>
Remote Re-energise Service	<u>D9</u>

2.2.5 Western Power specifies 16 standard metering services as reference services:



EDM 44531823 Page 11

Table 2.5: Standard metering services

Table 21: Standard metering services

Reference service name	Short name
Unidirectional, accumulation, bi-monthly, manual	<u>M1</u>
Unidirectional, accumulation (TOU), bi-monthly, manual	<u>M2</u>
Unidirectional, interval, bi-monthly, manual	<u>M3</u>
Unidirectional, interval, monthly, manual	<u>M4</u>
Unidirectional, interval, bi-monthly, remote	<u>M5</u>
Unidirectional, interval, monthly, remote	<u>M6</u>
Unidirectional, interval, daily, remote	<u>M7</u>
Bidirectional, accumulation, bi-monthly, manual	<u>M8</u>
Bidirectional, accumulation (TOU), bi-monthly, manual	<u>M9</u>
Bidirectional, interval, bi-monthly, manual	<u>M10</u>
Bidirectional, interval, monthly, manual	<u>M11</u>
Bidirectional interval, bi-monthly, remote	<u>M12</u>
Bidirectional, interval, monthly, remote	<u>M13</u>
Bidirectional, interval, daily, remote	<u>M14</u>
Unmetered supply, accumulation, bi-monthly, manual	<u>M15</u>
One off manual interval read	<u>M16</u>

2.2.72.2.6 Appendix E of this access arrangement provides details of each reference service, including:

- a description of the *reference service*;
- the *user* eligibility criteria;
- the applicable *reference tariff*;
- the applicable *standard access contract*; and
- the applicable *service standard benchmark*.

2.3 Payment by users

2.3.1 *Users* are required to pay a *charge* for *reference services* calculated by applying the related *reference tariffs*.



3 Excluded services

3.1 Purpose

3.1.1 This section of the *access arrangement* describes the *excluded services* offered by Western Power.

3.2 Excluded services

3.2.1 There are no *excluded services* at the *revisions commencement date* of this *access arrangement*. In accordance with section 6.35 of the *Code*, Western Power may at any time request the *Authority* to determine under section 6.33 of the *Code* that one or more *services* provided by means of the *Western Power Network* are *excluded services*.



4 Service standard benchmarks

4.1 Purpose

4.1.1 Pursuant to section 5.1(c) of the *Code*, this section provides the *service standard benchmarks* applicable to the *reference services*. *Service standard benchmarks* are not applicable to *non-reference services*.

4.2 Service standard benchmarks for distribution reference services

- 4.2.1 For the *reference services* A1 to A10, B1 and, C1 to CA1 to A10, A12 to A17, B1 and B3, C1 to C48 and D1 toand D4215 and any applicable ancillary *reference service* D2 to D7, the *service standard benchmarks* are expressed in terms of System Average Interruption Duration Index (SAIDI), System Average Interruption Frequency Index (SAIFI) and call centre performance.
- 4.2.2 In <u>clausessections</u> 4.2.3 and 4.2.5 **"distribution customer"** means a *consumer* connected to the *distribution system*.

System Average Interruption Duration Index (SAIDI)

4.2.3 SAIDI is applied as follows:

Table 4.15: Application of SAIDI

Table 22: Application of SAIDI

	System Average Interruption Duration Index (SAIDI) CBD Urban Rural Short Rural Long
Unit of Measure	Minutes per year.
Definition	Over a 12 month period, the sum of the duration of each sustained (greater than 1 minute) <i>distribution customer</i> interruption (in minutes) attributable to the <i>distribution system</i> (after exclusions) divided by the number of <i>distribution customers</i> served, that is:
	 <u>Sustained distribution customer interruption durations</u> Number of distribution customers served Where: A CBD feeder is a feeder supplying predominantly commercial, high-rise buildings, supplied by a predominantly underground distribution system containing significant interconnection and redundancy when compared to urban areas.



	System Average Interruption Duration Index (SAIDI) CBD Urban Rural Short Rural Long
	 An Urban feeder is a feeder, which is not a CBD feeder with actual maximum demand over the reporting period per total high voltage feeder route length greater than 0.3 MVA/km. A Rural Short feeder is a feeder which is not a CBD or urban feeder with a total high voltage feeder route length less than 200 km. A Rural Long feeder is a feeder which is not a CBD or urban feeder with a total high voltage feeder route length greater than 200 km. A Rural Long feeder is a feeder which is not a CBD or urban feeder with a total high voltage feeder route length greater than 200 km. The number of <i>distribution customers</i> served is determined by averaging the start of month values for the 12 months included in the 12 month period.
Exclusions	 One or more of: For an <u>unplanned</u> interruption on the <i>distribution system</i>, a day on which the major event day threshold, <u>determined in accordance with IEEE1366-2003 definitions</u> applying the "2.5 beta method", is exceeded. <u>This method excludes events which are more than 2.5 standard deviations greater than the mean of the log normal distribution of five financial years of SAIDI data. The major event day threshold is determined at the end of each financial year for use in the next financial year. The data set comprises daily unplanned SAIDI calculated over the five immediately preceding financial years after exclusions (below) are applied. Where the logarithms of the data set are not normally distributed, the Box-Cox transformation will be applied to reach a better approximation of the normal distribution.</u> Interruptions shown to be caused by a fault or other event on the <i>transmission system</i>. Interruptions shown to be caused by a fault or other event on a third party system (for instance, without limitation, interruptions caused by an intertrip signal, generator unavailability or a consumer installation). Planned interruptions caused by scheduled <i>works</i>. <i>Force majeure</i> events affecting the <i>distribution system</i>.

4.2.4 The service standard benchmarks expressed in terms of SAIDI for the reference services <u>A1</u> to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7A1 to A10, B1 and, C1 to C48 and D1 to and D42 for each year of this access arrangement period are shown in the following table:



 Table 4.26: SAIDI service standard benchmarks for reference services A1 to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7A1 to A10, B1 and, C1 to C4-8 and D1 to and D42

Table 23: SAIDI service standard benchmarks for reference services A1 to A8, A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7

SAIDI	For each<u>the</u> financial year ending 30 June <u>2018</u>	For the each financial year ending 30 June 2019 and each financial year thereafter
CBD	39.9	<u>33.737.2</u>
Urban	183.0	<u>130.6134.7</u>
Rural Short	227.8	<u>215.4226.3</u>
Rural Long	724.8	<u>848.3902.9</u>

System Average Interruption Frequency Index (SAIFI)

4.2.5 SAIFI is applied as follows:

Table 4.37: Application of SAIFI

Table 24: Application of SAIFI

	System Average Interruption Frequency Index (SAIFI) CBD Urban Rural Short Rural Long	
Unit of Measure	InterruptionsSustained interruptions per year.	
Definition	Over a 12 month period, the number of sustained (greater than 1 minute) <i>distribution customer</i> interruptions (number) attributable to the <i>distribution system</i> (after exclusions) divided by the number of distribution customers served, that is:	
	Number of sustained distribution customer interruptions	
	Number of distribution customers served	
	where:	
	• A CBD feeder is a feeder supplying predominantly commercial, high-rise buildings, supplied by a predominantly underground <i>distribution system</i> containing significant interconnection and redundancy when compared to urban areas.	
	• An Urban feeder is a feeder, which is not a CBD feeder, with actual maximum demand over the reporting period per total high voltage feeder route length greater than 0.3 MVA/km.	
	• A Rural Short feeder is a feeder which is not a CBD or urban feeder with a total high voltage feeder route length less than 200 km.	
	• A Rural Long feeder is a feeder which is not a CBD or urban feeder with a total high voltage feeder route length greater than 200 km.	



	System Average Interruption Frequency Index (SAIFI) CBD Urban Rural Short Rural Long • The number of distribution customers served is determined by averaging
	the start of month values for the 12 months included in the 12 month period.
Exclusions	 One or more of: For <u>unplanned</u> interruptions on the <i>distribution system</i>, a day on which the major event day threshold, determined in accordance with IEEE1366-2003 definitions applying the "2.5 beta method", is exceeded.
	This method excludes events which are more than 2.5 standard deviations greater than the mean of the log normal distribution of five financial years of SAIDI data. The major event day threshold is determined at the end of each financial year for use in the next financial year. The data set comprises daily unplanned SAIDI calculated over the five immediately preceding financial years after exclusions (below) are applied. Where the logarithms of the data set are not normally distributed, the Box-Cox transformation will be applied to reach a better approximation of the normal distribution.
	• Interruptions shown to be caused by a fault or other event on the <i>transmission system</i> .
	• Interruptions shown to be caused by a fault or other event on a third party system (for instance, without limitation interruptions caused by an intertrip signal, generator unavailability or a consumer installation).
	 Planned interruptions caused by scheduled <i>works</i>. <i>Force majeure</i> events affecting the <i>distribution system</i>.

<u>4.2.6</u> The service standard benchmarks expressed in terms of SAIFI for the reference services <u>A1</u> to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7A1 to A10, B1 and, C1 to C48 and D1 toand D42 for each year of this access arrangement period <u>areis</u> shown in the following table:

 Table 4.48: SAIFI service standard benchmarks for reference services A1 to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7A1 to A10, B1 and, C1 to C48 and D1 to and D42

 Table 25: SAIFI service standard benchmarks for reference services A1 to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7

	SAIFI	For <u>eachthe</u> financial year ending 30 June <u>2018</u>	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
	CBD	0.26	<u>0.210.23</u>
	Urban	2.12	<u>1.271.33</u>
	Rural Short	2.61	<u>2.342.38</u>



EDM 44531823 Page 17

SAIFI	For each <u>the</u> financial year ending 30 June <u>2018</u>	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
Rural Long	4.51	<u>5.705.90</u>

4.2.64.2.7 For the purpose of this *access arrangement*, the definitions of CBD, Urban, Rural Short and Rural Long feeder classifications are consistent with those applied by the Steering Committee on National Regulatory Reporting Requirements (SCNRRR).

Call centre performance

<u>4.2.8</u> Call centre performance is applied as follows:

4.2.7—

Table 4.59: Application of call centre performance

Table 26: Application of call centre performance

	Call centre performance	
Unit of Measure	Percentage of calls per year.	
Definition	Over a 12 month period, in relation to interruptions and life threatening emergencies, percentage of calls responded to in 30 seconds or less (after exclusions), that is:	
	Number of fault calls responded to in 30 seconds or less	
	Total Number of fault calls	
	where:	
	(a) "Number of fFault calls" responded to in 30 seconds or less" is:	
	 unless paragraph (a)(ii) applies, where the caller's postcode is automatically determined or when a valid postcode is entered by the caller, the number of fault calls where a recorded message commences within 30 seconds from that determination or entry; or 	
	 (ii) where the call is placed in the queue to be responded to by a human operator, the number of fault calls where the human operator commences to speak with the caller within 30 seconds of that placement. 	
	(b) A "fault call" is a telephone call from a caller entering the fault line or life threatening emergency line.	
	(c) A call may be placed in a queue to be responded to by a human operator when the caller:	
	 (i) chooses to hold (when invited to do so) at the end of the recorded message; 	
	(ii) chooses to hold (when invited to do so) rather than enter a postcode when prompted to do so; or	



	Call centre performance	
	(iii) enters an invalid postcode.	
	(d) For a call to be counted as being responded to under paragraph (a), the caller must receive from the recorded message or the human operator information regarding power interruptions in their area and related restoration information.	
	(e) A call where the interactive message service fails to automatically determine the caller's postcode or invite the entry of a postcode, as a result of which the service of providing information regarding power interruptions in their area and related restoration information does not commence, will be counted as a fault call not responded to in 30 seconds or less.	
Exclusions	One or more of:	
	• Calls abandoned by a caller in 4 seconds or less of their postcode being automatically determined or when a valid postcode is entered by the caller.	
	• Calls abandoned by a caller in 30 seconds or less of the call being placed in the queue to be responded to by a human operator.	
All telephone calls received on a major event day which is e SAIDI and SAIFI.		
	• A fact or circumstance beyond the control of Western Power affecting the ability to receive calls to the extent that Western Power could not contract on reasonable terms to provide for the continuity of service.	

4.2.9 The service standard benchmarks expressed in terms of call centre performance for the reference services A1 to A10, A12 to A17, B1 and B3, C1 to C15 and any applicable ancillary reference service D2 to D7A1 to A10, B1 and, C1 to C48 and D1 to and D42 for each year of this access arrangement period areis shown in the following table:

Table 27: Call centre service standard benchmarks for reference services A1 to A10, A12 to A17, B1 and B3, C1 to C15 and
any applicable ancillary reference service D2 to D7

	For eachthe financial year ending 30 June 2018	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
Call centre performance	77.5%	<u>86.8%85.3%</u>

4.3 Service standard benchmarks for transmission reference services

4.3.1 For the *reference services* A11 and B2<u>and any applicable ancillary *reference service* D2 to D7, the *service standard benchmarks* are expressed in terms of circuit availability, system minutes interrupted, system minutes interrupted, loss of supply event frequency and average outage duration.</u>



Circuit availability

4.3.2 Circuit availability is applied as follows:

Table 4.711: Application of circuit availability

Table 28: Application of circuit availability

	Circuit availability	
Unit of Measure	Percentage of hours per year.	
Definition	Over a 12 month period, the actual hours transmission circuits are available divided by the total possible hours available for transmission circuits (after exclusions), that is:	
	Number of hours transmission circuits are available × 100	
	Total possible hours available for transmission circuits	
	where:	
	• A "transmission circuit" is an arrangement of primary transmission elements on the <i>transmission system</i> that is overhead lines, underground cables, and bulk transmission power transformers used to transport electricity.	
Exclusions	One or more of:	
	Zone substation power transformers.	
	• Interruptions affecting the <i>transmission system</i> shown to be caused by a fault or other event on a third party system (for instance, without limitation interruptions caused by an intertrip signal, generator unavailability or a consumer installation).	
	• Force majeure events affecting the transmission system.	
	• Hours exceeding 14 days for planned interruptions for major construction <i>work</i> .	

<u>4.3.3</u> The service standard benchmarks expressed in terms of circuit availability for the reference services A11 and B2 and any applicable ancillary reference service D2 to D7 for each year of this access arrangement period areis shown in the following table:

4.3.3

 Table 4.812: Circuit availability service standard benchmarks for reference services A11 and B2 and any applicable

 ancillary reference service D2 to D7

 Table 29: Circuit availability service standard benchmarks for reference services A11 and B2 and any applicable ancillary

 reference service D2 to D7

	For each <u>the</u> financial year ending 30 June <u>2018</u>	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
Circuit availability	97.7%	<u>97.8%97.6%</u>

System minutes interrupted



System minutes interrupted is applied as follows:

Table 13: Application of system minutes interrupted

	System minutes interrupted	
	Meshed Radial	
	Radial	
Unit of Measure	Minutes per year.	
Definition	Over a 12 month period:	
	minutes) of Unserved energy at substations which are connected to the	
	Meshed transmission network divided by the System Peak MW; and	
	— System minutes interrupted Radial is the summation of MW (in minutes)	
	of Unserved energy at substations which are connected to the Radial	
	transmission network divided by the System Peak MW,	
	that is, for both Meshed and Radial transmission network separately:	
	5 MW (in minutes) of Unserved Energy	
	System Peak MW	
	where:	
	all overhead lines, underground cables, power transformers, reactive	
	compensation circuits and transmission zone substation equipment) for	
	unplanned events including extreme events, but not including the events	
	defined as exclusions.	
	for the previous financial year.	
Exclusions	One or more of:	
	<u>Momentary interruptions (less than one minute).</u>	
	<u>Unregulated transmission assets.</u>	
	fault or other event on a third party system (for instance, without	
	limitation interruptions caused by an intertrip signal, generator	
	unavailability or a consumer installation).	

The service standard benchmarks expressed in terms of system minutes interrupted for the reference services A11 and B2 for each year of this access arrangement period are shown in the following table:

Table 14: System minutes interrupted service standard benchmarks for reference services A11 and B2

System minutes interrupted	For the financial year ending 30 June	For each financial year ending 30 June thereafter
Meshed	<u>12.5</u>	<u>17.3</u>
Radial	<u>5.0</u>	<u>9.4</u>



Loss of supply event frequency

4.3.4 Loss of supply event frequency is applied as follows:

Table 4.915: Application of loss of supply event frequency

Table 30: Application of loss of supply event frequency

	Loss of supply event frequency
	>0.1 <u>and ≤1.0</u> system minutes interrupted
	>1.0 system minutes interrupted
Unit of Measure	Number of events per year.
Definition	Over a 12 month period, the frequency of Unplanned customer outage events where loss of supply:
	 <u>exceeds 0.1 system minutes interrupted and less than or equal to 1.0</u> system minutes interrupted; or
	• <u>e</u> xceeds 1.0 system minutes interrupted.
	System minutes are calculated for each supply interruption by the "load integration method" using the following formula, that is:
	∑ (MWh unsupplied x 60)
	System Peak MW
	where:
	• "Unplanned customer outages" relates to unplanned customer outages occurring on all parts of the regulated <i>transmission system</i> .
	 "MWh unsupplied" is the energy not supplied as determined by using Western Power metering and PI server database. This data is used to estimate the profile of the load over the period of the interruption by reference to historical load data.
	 Period of the interruption starts when a loss of supply occurs and ends when Western Power offers supply restoration to the customer.
	• For the financial year ending 30 June 2018, "System Peak MW" is the maximum peak demand recorded for the South West Interconnected System for the previous financial year.
	• For the financial year ending 30 June 2019 and each financial year thereafter, "System Peak MW" is the maximum peak demand recorded for the South West Interconnected System for the previous financial year, excluding the coincident demand for those customers receiving a <i>non-</i> <i>reference service</i> where the impact of an Unplanned customer outage event is excluded for the purpose of this measure.
Exclusions	One or more of:
	Planned interruptions_
	• Momentary interruptions (less than one minute).
	Unregulated transmission assets.
	 Interruptions affecting the <i>transmission system</i> shown to be caused by a fault or other event on a third party system (for instance, without limitation interruptions caused by an intertrip signal, generator unavailability or a consumer installation).
	• Force majeure events affecting the transmission system.



<u>4.3.5</u> The service standard benchmarks expressed in terms of loss of supply event frequency for the reference services A11 and B2 and any applicable ancillary reference service D2 to D7 for each year of this access arrangement period iares shown in the following table:

4.3.5

 Table 4.1016: Loss of supply event frequency service standard benchmarks for reference services A11 and B2 and any

 applicable ancillary reference service D2 to D7

Table 31: Loss of supply event frequency service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7

Loss of supply event frequency	For each<u>the</u> financial year ending 30 June <u>2018</u>	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
> 0.1 system minutes interrupted_and ≤1.0 system minutes interrupted	33	<u>2627</u>
> 1.0 system minutes interrupted	4	<u>746</u>



Average outage duration

4.3.6 Average outage duration is applied as follows:

Table 4.1117: Application of average outage duration

Table 32: Application of average outage duration

	Average outage duration	
Unit of Measure	Minutes per year.	
Definition	Over a 12 month period, the accumulative actualsum of the duration (in minutes) of all_Unplanned outages divided by the total Number of events on regulated transmission circuits (after exclusions), that is:	
	<u>S Aggregate dDuration (in minutes) of all Unplanned outages</u>	
	Total Number of events	
	where:	
	• "Unplanned outages" relates to interruptions occurring on all parts of the regulated <i>transmission system</i> .	
	• "Number of events" includes all forced and fault interruptions whether or not loss of supply occurs.	
	• A "transmission circuit" is an arrangement of primary transmission elements on the <i>transmission system</i> that is overhead lines, underground cables, and bulk transmission power transformers used to transport electricity.	
Exclusions	One or more of:	
	Planned interruptions.	
	Momentary interruptions (less than one minute).	
	Unregulated transmission assets.	
	• Zone substation power transformers and rReactive compensation plant.	
	• Interruptions affecting the <i>transmission system</i> shown to be caused by a fault or other event on a third party system (for instance, without limitation interruptions caused by an intertrip signal, generator unavailability or a consumer installation).	
	• Force majeure events affecting the transmission system.	
	• The impact of each event is capped at 14 days.	

4.3.7 The service standard benchmarks expressed in terms of average outage duration for the reference services A11 and B2 and any applicable ancillary reference service D2 to D7 for each year of this access arrangement period is shown in the following table:



 Table 4.1218: Average outage duration service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7

Table 33: Average outage duration service standard benchmarks for reference services A11 and B2 and any applicable ancillary reference service D2 to D7

	For each<u>the</u> financial year ending 30 June <u>2018</u>	For the financial year ending 30 June 2019 and each financial year thereafter For each financial year ending 30 June thereafter
Average outage duration	886	<u>1,2341,333</u>

4.4 Service standard benchmarks for street lighting reference services

4.4.1 For the *reference service* A9, the *service standard benchmarks* are expressed in terms of street lighting repair time.

Street lighting repair time

4.4.2 Street lighting repair time is applied as follows:

Table 4.1319: Application of street lighting repair time

Table 34: Application of street lighting repair time

	Street lighting repair time Metropolitan area Regional area	
Unit of Measure	Average number of <i>business days.</i>	
Definition	Over a 12 month period, average number of <i>business days</i> to repair faulty streetlights is the sum of the number of <i>business days</i> to repair each faulty streetlight divided by the number of faulty streetlights repaired (after exclusions).	
	5 Number of <i>business days</i> to repair each faulty streetlight	
	Number of faulty streetlights repaired	
	where:	
	• In calculating the number of <i>business days</i> to repair a faulty streetlight, the first <i>business day</i> is:	
	 where a faulty streetlight is detected by, or reported to, Western Power on a <i>business day</i>, the next <i>business day</i>; or 	
	 where a faulty streetlight is detected by, or reported to, Western Power on a day that is not a <i>business day</i>, the second <i>business day</i> after that day. 	
	• In calculating the number of <i>business days</i> to repair a faulty streetlight, the <i>business day</i> a fault is repaired is included (subject to the next point) even if the repair is effected part way through that <i>business day</i> .	
	• In calculating the number of <i>business days</i> to repair a faulty streetlight:	



	Street lighting repair time Metropolitan area Regional area	
	 where a faulty streetlight is detected by, or reported to, Western Power on a <i>business day</i> and the repair is effected on that <i>business day</i>, that <i>business day</i> is included as zero; 	
	 where a faulty streetlight is detected by, or reported to, Western Power on a day that is not a <i>business day</i> and the repair is effected on the next <i>business day</i>, that <i>business day</i> is included as zero. 	
	The period of a <i>business day</i> is the time period from one midnight to the following midnight.	
	• A "faulty streetlight" is defined by a recorded fault report.	
	• Metropolitan area means the areas of the State defined in Part 1.5 of the Code of Conduct for the Supply of Electricity to Small Use Customers 20 <u>1</u> 8.	
	• Regional area means all areas in the <i>Western Power Network</i> other than the metropolitan area.	
	Note:	
	• If a given streetlight is the subject of more than one fault report for the same fault, then only one fault report is recorded.	
	• If a given streetlight is the subject of multiple fault reports that relate to different faults then one report relating to each distinct fault is recorded.	
Exclusions	Force majeure events.	
	• Streetlights for which Western Power is not responsible for streetlight maintenance.	

4.4.3 The *service standard benchmarks* for the *reference service* A9 for each year of this *access arrangement period* are set out in the following table:

 Table 4.1420: Street lighting repair time service standard benchmark for reference service A9

Table 35: Street lighting repair time service standard benchmark for reference service A9

Region	For each financial year ending 30 June
Metropolitan area	5 <u>business</u> days
Regional area	9 <u>business</u> days

4.5 Service standard benchmark for supply abolishment reference service

4.5.1 For the *reference service* D1, the *service standard benchmark* is expressed in terms of response time.

Supply abolishment (whole current meter) response time

4.5.2 Supply abolishment response time is applied as follows:



Table 4.15: Application of supply abolishment (whole current meter) response time

Table 36: Application of supply abolishment (whole current meter) response time

	Supply abolishment (whole current meter) response time	
Unit of Measure	Average number of business days.	
Definition	Over a 12 month period, average number of <i>business days</i> to abolish supply is the sum of the number of <i>business days</i> to abolish supply for all supply abolishment requests, divided by the number of supply abolishment requests made (after exclusions). ∑ Number of <i>business days</i> to abolish supply for all supply abolishment requests Number of supply abolishment requests	
	where:	
	 In calculating the number of <i>business days</i> to abolish supply, the first <u>business day is:</u> 	
	 where a supply abolishment request is made by a user to Western Power before 3:00 PM on a business day, the next business day; or 	
	 where a supply abolishment request is made by a user to Western Power on a day that is not a business day, or after 3:00 PM on a business day, the second business day after that day. 	
	In calculating the number of <i>business days</i> to abolish supply:	
	 the business day supply is abolished is included (subject to the next point) even if the abolishment is performed part way through that business day; and 	
	 where a supply abolishment request is made by a user to Western Power on a business day and the abolishment is performed on that business day, that business day is counted as zero; or 	
	 where a supply abolishment request is made by a user to Western Power on a day that is not a business day, or after 3:00 PM on a business day, and the abolishment is performed on the next business day, that business day is counted as zero. 	
	A "supply abolishment request" is defined as an electricity transfer application for a supply abolishment in accordance with the <i>Applications</i> and Queuing Policy containing all information that Western Power, as a regsonable and prudent person, requires to abolish supply	
	 "Abolish supply" is defined as the time when the permanent disconnection of supply and the removal of the <i>meter</i> is completed. 	
Exclusions	Supply abolishment requests that:	
	 <u>o are cancelled or are requested to be deferred;</u> <u>o relate to non-standard technical configurations, site access issues or safety issues;</u> <u>o require external approvals or actions beyond the control of Western Power as a <i>reasonable and prudent person;</i> or</u> 	
	• A fact or circumstance beyond the control of Western Power as a <i>reasonable and prudent person</i> affecting the ability to abolish supply.	



	Supply abolishment (whole current meter) response time
	Force majeure events affecting the ability to abolish supply.

4.5.3 The service standard benchmarks for the reference service D1 for each year of this access arrangement period are set out in the following table:

Table 37: Supply abolishment (whole current meter) response time service standard benchmark for reference service D1

	For each financial year ending 30 June
Supply abolishment (whole current meter) response time	<u>15 business days</u>

4.6 Service standard benchmarks for remote de-energise and remote re-energise reference services

- 4.6.1 For the *reference service* D8 and D9, the *service standard benchmarks* are expressed in terms of response time.
- 4.6.2 These service standard benchmarks only come into effect once the remote de-energise and remote re-energise reference services are provided to one or more users.

Remote de-energise response time

4.6.3 Remote de-energise response time is applied as follows:

Table 38: Application of remote de-energise response time

-	Remote de-energise response time	
Unit of Measure	Average number of business days.	
Definition	 Over a 12 month period, average number of <i>business days</i> to remotely <u>de-energise is the sum of the number of <i>business days</i> to remotely de- <u>energise a meter for all remote de-energise requests, divided by the</u> <u>number of remote de-energise requests made (after exclusions).</u></u> <u>Σ Number of <i>business days</i> to remotely de-energise for all remote de-energise requests</u> 	
	Number of remote de-energise requests where:	
	In calculating the number of <i>business days</i> to remotely de-energise, the <u>first <i>business day</i> is:</u>	
	 where a remote de-energise request is made by a user to Western Power before 12 noon on a business day, the next business day; or 	



_	Remote de-energise response time		
	 where a remote de-energise request is made by a user to Western Power on a day that is not a business day, or after 12 noon on a business day, the second business day after that day. 		
	Fridays and the <i>business days</i> occurring before a <i>public holiday</i> are not calculated as <i>business days</i> in relation to this measure.		
	In calculating the number of <i>business days</i> to remotely de-energise: <u>o the <i>business day</i> the remote de-energise is performed is</u> <u>included, even if the remote de-energise is performed part</u>		
	 way through that business day; and where a remote de-energise request is made by a user to Western Power on a business day and the remote de- energise is performed on that business day, that business day is counted as zero; or 		
	 where a remote de-energise request is made by a user to Western Power on a day that is not a business day, or after 12 noon on a business day, and the remote de-energise is performed on the next business day, that business day is counted as zero. 		
	• A "remote de-energise" is defined as the time when supply voltage is removed from all outgoing circuits from the <i>meter</i> on a non-permanent basis by a command sent to a <i>meter</i> from a remote locality.		
Exclusions	Remote de-energise requests that are cancelled or are requested to be <u>deferred.</u> Bemete de energisation requests received en a business day in relation to		
	this measure, where the total number of de-energisation requests exceeds the maximum operational capacity of the infrastructure supporting the remote de-energisation requests.		
	A fact or circumstance beyond the control of Western Power as a reasonable and prudent person affecting the ability to remote de- energise.		
	 Force majeure events anecting the remote de-energise service. 		

<u>4.6.4</u> The service standard benchmark for the reference service D8 for each year of this access arrangement period is set out in the following table:

Table 39: Remote de-energise response time service standard benchmark for reference service D8

	For each financial year ending 30 June
Remote de-energise	<u>1 business day</u>
response time	

Remote re-energise response time

4.6.5 Remote re-energise response time is applied as follows:



Table 40:	Application	of remote	re-energise	response time

_	Remote re-energise response time
Unit of Measure	Average number of business days.
<u>Definition</u>	Over a 12 month period, average number of <i>business days</i> to remotely re- energise is the sum of the number of <i>business days</i> to remotely re-arm a previously de-energised <i>meter</i> for all remote re-energise requests, divided by the number of remote re-energise requests made (after exclusions). S Number of <i>business days</i> to remotely re-arm for all remote re-energise requests Number of remote re-energise requests
	where:
	In calculating the number of <i>business days</i> to remotely re-energise, the first <i>business day</i> is:
	 where a remote re-energise request is made by a user to Western Power before 12 noon on a business day, the next business day; or
	 where a remote re-energise request is made by a user to Western Power on a day that is not a business day, or after 12 noon on a business day, the second business day after that day.
	In calculating the number of <i>business days</i> to remotely re-energise:
	 the business day the remote re-energise is performed is included, even if the remote re-energise is performed part way through that business day; and
	 where a remote re-energise request is made by a user to Western Power on a business day and the remote re- energise is performed on that business day, that business day is counted as zero; or
	 where a remote re-energise request is made by a user to Western Power on a day that is not a <i>business day</i>, or after 12 noon on a <i>business day</i>, and the remote re-energise is performed on the next <i>business day</i>, that <i>business day</i> is counted as zero
	 A "remote re-energise" is defined as the time when a previously de- energised meter is re-armed by a command sent to that meter from a remote locality.
Exclusions	Remote re-energise requests that are cancelled or are requested to be <u>deferred.</u>
	Remote re-energisation requests received on a <i>business day</i> in relation to this measure, where the total number of re-energisation requests exceeds the maximum operational capacity of the infrastructure supporting the remote re-energisation requests
	A fact or circumstance beyond the control of Western Power as a <u>reasonable and prudent person</u> affecting the ability to remote re- <u>energise.</u>
	Force majeure events affecting the remote re-energise service.



<u>4.6.6</u> The service standard benchmark for the reference service D9 for each year of this access arrangement period is set out in the following table:

	For each financial year ending 30 June
Remote re-energise response time	<u>1 business day</u>

Table 41: Remote re-energise response time service standard benchmark for reference service D9

4.54.7 Exclusions

- 4.5.14.7.1 In each of the *service standard benchmarks* there is a definition of the measure and stated exclusions. Each exclusion is a circumstance in relation to which, when it occurs, the resulting units are not included in the measure. For example, for SAIDI, when a *force majeure* event occurs the duration of the related interruption in minutes is not included in the calculation of the measure.
- <u>4.7.2</u> Whether or not particular circumstances meet the criteria to be an exclusion, such that the resulting units are not included in the measure, may be considered by the *Authority* when it *publishes* Western Power's actual *service standard* performance against the *service standard benchmarks* under section 11.2 of the *Code*. Where the *Authority* accepts an exclusion in such a report, it will be an exclusion for the purposes of the application of this *access arrangement* and the *Code*.
- <u>4.7.3</u> Where Western Power has applied a Box-Cox transformation method to the daily unplanned SAIDI data set to determine the major event day threshold, in the *service standard performance report* provided for the financial year in which the major event day threshold is used, Western Power must:
 - a) Demonstrate that the natural logarithm of the data set of each unplanned SAIDI value is not normally distributed.
 - b) Provide the calculations that demonstrate the application of the Box-Cox transformation method to the unplanned SAIDI values.
 - <u>c)</u> Provide the data set resulting from applying the Box-Cox transformation <u>method.</u>
 - d) Demonstrate that the resulting data set is normally distributed or that the normality of the data set is improved.



5 Price control

5.1 Overview of price control

5.1.1 In this access arrangement:

"non-revenue target cap services" means the following services:

- a) non-reference services provided by Western Power by means of the Western Power Network other than non-reference services that are provided as revenue captarget services;
- b) reference services described as reference services (ancillary) in Appendix E; and
- a)c) on and from 1 July 2020, reference service (metering) M16 as set out in Appendix E.-

"revenue captarget services" means the following *covered services* provided by Western Power by means of the *Western Power Network*:

- a) connection service;
- b) exit service;
- c) entry service;
- d) *bi-directional service* (within the meaning of section 2.2.1 of this *access arrangement*); and
- <u>e)</u> the metering *services* provided ancillary to the *services* in paragraphs (a) to
 (d) that are defined as standard metering services in the <u>MSLAmodel</u> <u>service level agreement most recent Model Service Level</u> <u>Agreementrecently approved by the Authority under the Electricity Industry</u> <u>(Metering Code 2005) 2012</u>;
- e)f) on and from 1 July 2020, *reference services* (metering) M1 to M15 as set out in Appendix E; and
- f)g)_streetlight maintenance.

5.1.2 In accordance with sections 6.1 and 6.2(c) of the *Code*:

- a) a *revenue cap<u>price control</u>* will apply to *revenue <u>captarget</u> services* that is set by reference to Western Power's *approved total costs*; and
- b) <u>subject to paragraph (c)</u>, charges for *non-revenue* <u>captarget</u> services will be:
 - i. any applicable lodgement fees payable under the Applications and Queuing <u>Policy;</u>

i-ii. a charge set out in the Price List for, reference service (metering) M16;

and if not provided for in the above instruments, then the charges will be;

ii.iii. negotiated in good faith;

iii.iv.consistent with the *Code objective*; and



v. reasonable; and

iv. .

- c) charges for access applications will be consistent with the Applications and Queuing Policy and charges for extended metering services (within the meaning of the MSLA) will be consistent with the MSLA and clause 6.6(1)(e) of the Electricity Industry (Metering) Code 2012.
- 5.1.3 Separate revenue capstargets will apply in respect of the *revenue cap-target* services provided by means of the *transmission system* and the *distribution system*. The establishment of each revenue captarget has been made by reference to Western Power's approved total costs for revenue-cap target services for each of the *transmission system* and the *distribution system*.
- 5.1.4 The calculation of Western Power's *approved total costs* for *revenue <u>captarget</u> services* has been undertaken in accordance with the building block method for each of the *transmission system* and the *distribution system*, as contained in the revenue model.
- 5.1.5 Despite section 1.3.1 of this access arrangement, the price control and all incentive and cost recovery mechanisms described in this access arrangement operate from 1 July 20122017, and therefore references to access arrangement period should be interpreted accordingly.

5.2 Capital base value

5.2.1 The tables below show the derivation of the *capital base* value as at 30 June <u>2012</u>2017.

Table 5.121: Derivation of Transmission Initial Capital Base (net) (\$ million real as at 30 June 2017)

Table 42: Derivation of Transmission Initial C	pital Base (net) (\$ million real as at 30 June 2017)

Financial year ending:	30 June 2009<u>2013</u>	30 June - 2010<u>2014</u>	30 June - 2011<u>2015</u>	30 June - <u>20122016</u>	<u>30 June</u> <u>2017</u>
Opening capital base value	<u>2,816.7</u>	<u>2,927.72,94</u> 2.8<u>28.6</u>319. 7	<u>3,161.63,16</u> <u>32,435.1<u>3,1</u> <u>77.6</u></u>	<u>3,197.53,19 9.23<u>3,215.4</u></u>	<u>3,135.53,13 8.0 3,156.0</u>
less depreciation	<u>94.0</u>	-74<u>103</u>.4	-79.5<u>114.1</u>	-90.0<u>121.3</u>	<u>129.4</u>
less accelerated depreciation	Ξ	0.0_	0.0_	0.0_	<u>-</u>
plus new facilities investment (net of capital contributions and asset disposals)	<u>204.9205.8 220.1</u>	<u>337.4338.0 338189.7</u>	<u>149.9150.0 151149.3</u>	<u>59.360.1</u> 61133.2	<u>102.6105.2 105.2</u>
plus investment from prior periodsClosing capital base value	<u>2,927.72,92 8.6 2,942.8</u>	<u>3,161.63,16 3.2 33,177.6</u>	<u>3,197.53,19 9.23<u>3,215.4</u></u>	<u>3,135.53,13</u> <u>8.06.5<u>3,156</u> <u>.0</u></u>	<u>3,108.63,11 3.8 3,131.8</u>



Financial year ending:	30 June - <u>20092013</u>	30 June - <u>20102014</u>	30 June - <u>20112015</u>	30 June - <u>2012</u> 2016	<u>30 June</u> <u>2017</u>
Opening capital base value	<u>4,248.7</u>	<u>4,708.54,7 07.844,709</u> <u>.9</u>	<u>5,142.95,14 2.33 ,276.5<u>,1</u>44.4</u>	<u>5,494.35,5</u> <u>04.453,538</u> . <u>15,506.4</u>	<u>5,723.15,74 6.2 5,752.6</u>
less depreciation	<u>214.0</u>	- 152.7 236.2	-166.0 261.9	- 183.6 266.5	<u>281.5</u>
less accelerated depreciation	<u>3.8</u>	<u>-4.10.5</u>	- 4.1	- 3.9	±.
plus new facilities investment (net of capital contributions and asset disposals)	<u>677.6676.9 679.0</u>	<u>671.1671.2 671430.3</u>	<u>613.3624.0</u> 624431.7	<u>495.2508.4 512502.9</u>	<u>356.8362.3 363.8</u>
plus investment from prior periods Closing capital base value	<u>4,708.54,7 07.8 <u>4,709.9</u></u>	<u>5,142.95,1</u> 42.350.0 <u>5,</u> 144.4	<u>5,494.35,50 4.450.0<u>5,50</u> <u>6.4</u></u>	<u>5,723.15,7</u> <u>46.250.05,</u> <u>752.6</u>	<u>5,798.45,82 7.1 5,834.9</u>

Table 5.222: Derivation of Distribution Initial Capital Base (net) (\$ million real as at 30 June 2012201	4
Table 43: Derivation of Distribution Initial Capital Base (net) (\$ million real as at 30 June 2017)	

- 5.2.2 The *capital base* value as at 30 June 2012 reflects a forecast of *new facilities investment* for the year ending 30 June 2012 (2011/12) and a forecast of inflation of 1.25% for the year ending 30 June 2012. To ensure that Western Power is remunerated only for actual *new facilities investment* that is undertaken in the year ending 30 June 2012 and actual inflation, the opening *capital base* at the commencement of the next *access arrangement period* will be adjusted and the *target revenue* in the next *access arrangement period* will be adjusted as follows:
 - a) the capital base value at the commencement of the next access arrangement period will be adjusted (in real terms) for any difference between the actual new facilities investment and the forecast of new facilities investment for the 2011/12 year that was used to establish the opening capital base value at 30 June 2012 (the 2011/12 new facilities investment forecast error);
 - b) the capital base value at the commencement of the next access arrangement period will also be adjusted for any difference between the actual inflation (using the CPI) and the forecast inflation for the 2011/12 year that was used to establish the opening capital base value at 30 June 2012 (the 2011/12 inflation forecast error); and
 - c) an adjustment to the target revenue in the next access arrangement period will be made to compensate Western Power (or users) for the revenue foregone (or additional revenue recovered) by Western Power over this access arrangement period in respect of the 2011/12 new facilities investment forecast error and the 2011/12 inflation forecast error.

5.2.3 For the avoidance of doubt:

d) under the arrangements set out in section 5.2.2 of this access arrangement the target revenue for this access arrangement period will not be adjusted for the



EDM 44531823 Page 34 2011/12 new facilities investment forecast error or the 2011/12 inflation forecast error;

- e) the intended effect of the arrangements set out in section 5.2.2 of this access arrangement is to hold Western Power and users financially neutral in the event that there is a 2011/12 new facilities investment forecast error or 2011/12 inflation forecast error by taking account of:
 - i. the effects of actual inflation; and
 - ii. the time value of money as reflected by Western Power's weighted average cost of capital for the Western Power Network

and

adjustments made pursuant to section 5.2.2 of this *access arrangement* will have the effect of ensuring that the total revenue recovered by Western Power over this *access arrangement period* and subsequent *access arrangement periods* will be equivalent in present value terms to the amount that would be recovered if there were no 2011/12 new facilities investment forecast errors and no 2011/12 inflation forecast error.

5.3 Depreciation

- 5.3.1 Pursuant to section 6.70 of the *Code*, the *price control* set out in this *access arrangement* provides for the depreciation of the *network assets* that comprise the *capital base*. References to depreciation in this *access arrangement* relate solely to regulatory depreciation for the purposes of calculating the *target revenue*, and do not relate to the calculation of depreciation for accounting or taxation purposes.
- 5.3.2 The depreciation provision contained in the *target revenue* for each year of this *access arrangement period* is calculated using:
 - a) the straight line depreciation method;
 - b) the existing weighted average lives for each of the *transmission system* and *distribution system* that comprise the *capital base* value as at 30 June 20122017; and
 - c) for *new facilities investment* forecast for this *access arrangement period* the weighted average lives for each of the *transmission system* and *distribution system* based on the asset lives for each group of *network assets* as set out in the following tables:

Table 5.323: Transmission asset groupings and economic lives for depreciation purposes

Table 44: Transmission asset groupings and economic lives for depreciation purposes

Asset group	Economic Life (years) for depreciation purposes
Transmission transformers	50 years
Transmission reactors	50 years
Transmission capacitors	40 years
Transmission circuit breakers	50 years



Asset group	Economic Life (years) for depreciation purposes
Transmission lines – steel towers	60 years
Transmission lines - wood poles	45 years
Transmission cables	55 years
Transmission metering	40 years
Transmission SCADA and communications	11 years
Transmission IT	6 years
Transmission other, non-network assets	16.85<u>27</u> years

Table 5.424: Distribution asset groupings and economic lives for depreciation purposes

Table 45: Distribution asset groupings and economic lives for depreciation purposes

Asset group	Economic Life (years) for depreciation purposes
Distribution lines - wood poles	41 years
Distribution lines - steel poles	50 years
Distribution underground cables	60 years
Distribution transformers	35 years
Distribution switchgear	35 years
Street lighting	20 years
Distribution meters and services	25 <u>15</u> years
Distribution IT	6 years
Distribution SCADA & communications	10.16 years
Distribution other, non-network assets	<u>10.1627 years</u>

- 5.3.3 Western Power is not proposing any accelerated depreciation in this *access arrangement period* in relation to *network assets* for the *transmission system*. <u>or the *distribution*</u> <u>system</u>.
- 5.3.4In respect of network assets for the distribution system, Western Power will applyaccelerated depreciation in respect of those network assets that will be decommissionedas a result of the State Underground Power Program undertaken by Western Power onbehalf of the Western Australian government as set out in the following table:



EDM 44531823 Page 36
	<u>30 June</u> <u>2018</u>	<u>30 June</u> <u>2019</u>	<u>30 June</u> <u>2020</u>	<u>30 June</u> <u>2021</u>	<u>30 June</u> <u>2022</u>
Underground Cables	<u>3.63</u>	<u>4.84</u>	<u>3.25</u>	Ξ	Ξ
Transformers	_	Ξ	Ξ	Ξ	Ξ
Switchgear	<u>0.46</u>	<u>1.48</u>	<u>0.76</u>	Ξ	Ξ
Street lighting	<u>0.28</u>	<u>0.57</u>	<u>0.36</u>	Ξ	Ξ
Meters and Services	Ξ	Ξ	Ξ	Ξ	Ξ
<u>Π</u>	_	Ξ	Ξ	_	Ξ
SCADA & Communications	_	Ξ	Ξ	_	Ξ
Other Distribution Non-Network	-	-	-	-	-
Distribution Land & Easements	<u> </u>	=	_	-	_

Table 5.525: Distribution accelerated depreciation by asset class (\$ million real as at 30 June 2017)

Table 46: Distribution accelerated depres	sistion by assot class (\$ million roa	l as at 20 June 2017)
Table 46: Distribution accelerated deprec	clation by asset class (5 million rea	Tas at 50 June 2017

5.3.35.3.5 The depreciation of the opening *capital base* at the commencement of the next *access arrangement period* will be the forecast depreciation contained in the *target revenue* for the *is access arrangement period*.

5.4 Weighted average cost of capital

5.4.1 Pursuant to section 6.64 of the *Code* the *weighted average cost of capital* for the *Western* Power Network is 3.60% real post-tax. WACC_{NOM} for the financial year ending 30 June
 2018 and 30 June 2019 is 6.09125.87% nominal post tax-and for the financial year ending 30 June 2019 is 6.09%¹12% nominal post-tax, derived using the following formula:

$$WACC_{Nom} = r_e \times \frac{E}{E+D} + r_d \times \frac{D}{E+D}$$

where:

re is the cost of equity, being 7.246.9957%

 r_d is the cost of debt, being 5.324229% for the financial years ended 30 June 2018 and 5.324229% for the financial year ended 30 June 2019

<u>*E* is the proportion of equity used to finance regulated assets by a</u> <u>benchmark electricity network service provider (4045%)</u>

<u>*D* is the proportion of debt used to finance regulated assets by a benchmark electricity network service providers (6055%)</u>

5.4.2 The cost of debt (r_d) in section 5.4.15.4.25.4.1 will be updated annually to give effect to the annual update of the trailing average debt risk premium ("**DRP**"). The annual update

⁴ This figure (and the related figure for cost of debt (r_{d}) is a 'placeholder' and will be updated as part of the *approval* of the proposed access arrangement by the Authority.



of the cost of debt will give rise to an annual update of the weighted average cost of capital. The update of the DRP, cost of debt and weighted average cost of capital will apply to the financial years endeding 30 June 2019, 30 June 2020, 30 June 2021 and 30 June 2022.

5.4.3 The updated *DRP* and resulting updated *weighted average cost of capital* will be reflected in the update of the *price list* in accordance with sections 6.4.2 6.4.2 and 6.4.3.

Trailing average cost of debt variation

5.4.4 The annual update of the trailing average *DRP* in each relevant financial year of this *access arrangement period* is to be calculated by applying the following formula:

$$TA DRP_0 = \frac{\sum_{t=0}^{-9} DRP_t}{10}$$

where

 $TA DRP_0$ is the equally weighted trailing average of the DRP to apply in the following year as the annual update of the estimate used in the current year; and

 DRP_t is the DRP estimated for each of the 10 regulatory years

t = 0, -1, -2..., -9.

 DRP_t refers to the DRP estimates in each year = 0, -1, -2..., -9, which are either:

5.4.5 **t**The forward looking DRP estimators for the financial years endeding 30 June 2020, 30 June 2021 orand 30 June 2022 estimated during the 20 *business day* averaging period, using the Authority's bond yield method of automatic formulas as described in section 5.4.13 below ("Bond Yield Approach"); or

5.4.6 **t**The published *DRP*_t, estimates, derived as follows:

 <u>calendarfinancial year 2008/09: DRP_{2008/09}: 5.4835.525:</u> <u>3.76</u>-per cent (derived from the <u>Reserve Bank of Australia 10 year credit spread to swap interpolated daily data);</u>

____;

- <u>calendar financial year 2009/10: DRP_{2009/10}: 2.3554.622.509 per cent;</u>
- <u>calendar financial year 2010/11: DRP_{2010/11}: 1.8952.13005</u> per cent;
- <u>calendar financial year 2011/12: DRP_{2011/12}: 2.842</u>3.000: 2.38 per cent;
- <u>calendar financial year 2012/13: DRP_{2012/13}: 2.768</u>32.988: 3.17 per cent;
- <u>calendar financial year 2013/14: DRP_{2013/14}: 2.634</u>3.0416 per cent;
- <u>calendar financial year 2014/15: DRP_{2014/15}: 1.6401.770: 2.25-per cent;</u>



- <u>calendar financial year 2015/16: DRP_{2015/16}: 2.3522.07420 per cent;</u>
- <u>calendar financial year 2016/17: DRP_{2016/17}: 1.656: 2.56-per cent (derived from the</u> <u>Reserve Bank of Australia 10 year credit spread to swap for the period up to 31 May</u> <u>2016 and the Authority's Bond Yield Approach thereafter);</u>
- calendar financial year 2017/18: DRP_{2017/18}: 1.95241 per cent (applying the Authority's Bond Yield Approach for the period 1 January 2017 to 30 June 2017).;

-calendar year 2018: DRP₂₀₁₈: to be calculated prior to the *approval* of this access arrangement.

- 5.4.7 The trailing average *DRP* estimate for the financial year ending 30 June 2018 (TA DRP₂₀₁₈); will beis 2.796132.487%, being the average derived from DRP₂₀₀₈ to DRP₂₀₁₂-listed in section 5.4.4 above.
- 5.4.8 The trailing average *DRP* estimate for the financial year ending 30 June 2019 (TA DRP₂₀₁₉) will beis 2.4872.613%, being the average derived from DRP_{2008/09} to DRP_{2017/18} listed in section 5.4.6 above the average derived from DRP₂₀₀₉ to DRP₂₀₁₈ listed above.
- 5.4.9The first annual update of the DRP will apply for the financial year ending 30 June 2020.All annual updates of the DRP are to be determined consistent with the Bond Yield
Approach.
- 5.4.10The Authority required that Western Power nominate an averaging period for the
pruposes purposes of determining the DRP for each of the financial years ending 30 June
2020, 30 June 2021 and 30 June 2022. The averaging periods are a nominated 20 business
days (based on eastern statesNSW public holidays) during the period 1 January
September to 310 JanuaryApril in the financial year prior to the relevant financial year.
The nominated 20 business day averaging period does not need to be identical in each
year.
- 5.4.11The forward looking estimates of the DRP for each financial year ending 30 June 2020, 30June 2021 and 30 June 2022, will be estimated using the Bond Yield Approach. Resulting
estimates of the DRP will be included in the calculation of the trailing average DRP in
accordance with the formula in section 5.4.65.4.4
above.
 - The next DRP estimate that will be made will be based on the nominated 20 days falling in the period 1 September 2019 to 31 January 2020 (for DRP₂₀₂₀). That next DRP estimate will be incorporated in the trailing average DRP₂₀₂₀ (that is, TA DRP₂₀₂₀), and the updated weighted average cost of capital, which will then apply in the financial year 2020 by way of the price list update in section 6.4.36.4.3.
- 5.4.12 The following method of automatic formulas applies where the Authority's Bond Yield Approach is used for updating the estimates of the DRP, and will remain unchanged for the duration of this access arrangement period, and hence will apply for the estimates made for DRP₂₀₂₀, as well as for the estimates DRP₂₀₂₁ and DRP₂₀₂₂.



EDM 44531823 Page 39

5.4.13 The Authority's Bond Yield Approach consists of the following six processes:

a) Determining the Benchmark Sample

Identifying a sample of bonds based on the benchmark sample selection criteria. This will comprise a 'cross section' of bonds.

b) Collecting Data

<u>Collecting data for those bonds over the averaging period in question, for example 20</u> <u>trading days. This represents 'time series' data related to each bond.</u>

c) Converting Yields to Australian Dollar Equivalents

Converting yields for bonds denominated in foreign currencies into Australian dollar ("AUD") equivalents so that all yields are expressed as an AUD equivalent.

d) Averaging Yields over the Averaging Period

Calculating an average AUD equivalent bond yield for each bond in the cross section across the averaging period. For example, where a 20 trading day averaging period applies, each bond will have a single 20 day 'average yield' calculated.

e) Estimating 'Curves'

Estimating three yield curves based on different methodologies and using the average yield for each bond; its remaining term to maturity; and AUD face value.

f) Calculating the DRP

Calculating the DRP by subtracting the average of the 10 year AUD interest rate swap (IRS) rate from the 10 year cost of debt estimate, with the latter calculated as the average of the three estimated yield curves at the ten year tenor.

5.4.14 Each process is comprised of a series of automatic formulas that will be used for the annual updates of the *DRP*. Further details of the automatic update approach are set out in the *Authority's approval* of this access arrangement.

5.5 Deferred revenue from the second <u>and third</u> access arrangement period

- 5.5.1 Western Power deferred the recovery of some transmission and distribution revenue from the second *access arrangement period* to the third or subsequent *access arrangement periods*. <u>("initial deferred revenue")</u>.
- 5.5.2 The tables below show the derivation of the *deferred revenue* value as at 30 June 2012 to be recovered so that Western Power is financially neutral compared to a situation where *revenue* deferral had not occurred.

-<u>This access arrangement will defer additional transmission revenue from the fourth</u> access arrangement period to subsequent access arrangement periods ("additional transmission deferred revenue"). The table below shows the additional transmission deferred revenue



Financial year	3	3		. a	; <u> </u>
ending:	θ	0	e	e e) <u>C</u>
	f	f	f	f f	Ŧ
	н	H	ť	+ +	+ <u>+</u>
	n	n	f	+ f) <u>H</u>
	e	e	e	e e	e <u>e</u>
	2	2	2	- 2	<u>2</u>
	θ	θ	e	i e) <u>e</u>
	θ	1	4	- 4	- 2
	9	θ	1	. 2	2
	<u>2</u>	<u>2</u>	2		
	<u>0</u>	<u>0</u>	Ē	<u>e</u>	<u>)</u>
	<u>±</u>	<u>1</u>	2	- 2	
	<u>8</u>	<u>9</u>	Ē	1	
Opening <u>Addition</u> <u>al deferred</u> revenue value	<u></u>	5 2 2 5 4 6 9 - 6 5 4 : 4 : 2 : 2 : 2 : 2 : 2 : 2 : 5 4 6 9 : 6 5 4 : 5 4 : 5 4 : 6 9 : 5 4 : 5 : 4 : 5 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 4 : 5 : 5			
Closing deferred revenue value	69.6				

Table 26:_Derivation of <u>Additional transmission_system</u> **initial** deferred revenue (\$ million real as at 30 June 2012<u>2017</u>}



5.5.2 The tables below show the derivation of the *initial* deferred revenue value as at 30 June 2017 to be recovered so that Western Power is financially neutral compared to a situation where *initial* deferred revenue deferral had not occurred.

Table 5.627: Derivation of distribution transmission system initial deferred revenue (\$ million real as at 30 June 20122017)

Table 47: Derivation of transmission system deferred revenue (\$ million real as at 30 June 2017)

Financial year ending:	30 June 2009<u>2013</u>	30 June 2010<u>2014</u>	30 June 2011<u>2015</u>	30 June 2012 2016	<u>30 June</u> <u>2017</u>
Opening deferred revenue value	<u>96.7</u>	523.1 95.9	564.8 95.2	609.9 94.4	<u>93.6</u>
plus time value of money-less principal recovered	<u>0.7</u>	<u>410</u> .7	4 <u>5.1</u> 0.8	4 <u>8.7</u> 0.8	<u>0.8</u>
Closing deferred revenue value	523.1 <u>95.9</u>	564.8<u>95.2</u>	609.9 <u>94.4</u>	658<u>93</u>.6	<u>92.8</u>

Table 5.728: Derivation of distribution system initial deferred revenue (\$ million real as at 30 June 2017)

Table 48: Derivation of distribution system deferred revenue (\$ million real as at 30 June 2017)

Financial year ending:	<u>30 June</u> <u>2013</u>	<u>30 June</u> <u>2014</u>	<u>30 June</u> <u>2015</u>	<u>30 June</u> <u>2016</u>	<u>30 June</u> <u>2017</u>
Opening deferred revenue value	<u>726.1</u>	<u>718.5</u>	<u>710.6</u>	<u>702.3</u>	<u>693.9</u>
less principal recovered	<u>7.6</u>	<u>7.9</u>	<u>8.2</u>	<u>8.5</u>	<u>8.8</u>
Closing deferred revenue value	<u>718.5</u>	<u>710.6</u>	702.3	<u>693.9</u>	<u>685.0</u>

- 5.5.3 Western Power will recover the *initial-deferred revenue* amounts detailed in section 5.5.2 of this *access arrangement* as a real annuity amount over:
 - a) a 50 year period for the *transmission system* <u>initial</u> deferred revenue commencing 1 July 2012; and
 - b) a 42 year period for the *distribution system* <u>initial</u> deferred revenue commencing 1 July 2012.
- 5.5.4 The interest rate applicable for the calculation of the real annuity during this *access arrangement period* is the *weighted average cost of capital* for the *Western Power Network* as set out in section 5.4.1 of this *access arrangement*....

<u>Notwithstanding section 5.5.4, Western Power will further recover distribution system</u> initial deferred revenue in this access arrangement period equal to the additional transmission deferred revenue.



5.5.5 The amounts that will be added to the *target revenue* for the *transmission system* and *distribution system* and recovered during this *access arrangement period* are detailed in the table below.

 Table 5.829: Amount to be added to the target revenue due to the recovery of initial deferred revenue and additional

 transmission_deferred revenue (\$ million real as at 30 June 20122017)

 Table 49: Amount to be added to the target revenue due to the recovery of deferred revenue (\$ million real as at 30 June 2017)

Financial year ending:	30 June	30 June	30 June	30 June	30 June
	2013 2018	201 4 <u>2019</u>	2015 2020	2016 2021	2017<u>2022</u>
Transmission system	<u>4.4<mark>4.6</mark>44</u> .8	<u>4.44.6</u> 4 <u>4</u> .8	<u>4.44.6</u> 4 <u>4</u> .8	<u>4.44.644</u> .8	<u>4.44.6</u> 4 <u>4</u> .8
Distribution system	<u>35.636.8</u>	<u>35.636.8</u>	<u>35.636.8</u>	<u>35.636.8</u>	<u>35.636.8</u>
	30.7 <u>104.1</u>	30.7<u>92.1</u>	30.7 <u>82.2</u>	30.7<u>76.1</u>	30.7<u>68.2</u>

The deferred revenue value as at 30 June 2012 reflects a forecast of inflation of 1.25% for the year ending 30 June 2012. To ensure that Western Power is remunerated only for actual inflation, the *target revenue* in the next *access arrangement period* will be adjusted to compensate Western Power (or *users*) for the revenue foregone (or additional revenue recovered) by Western Power over this *access arrangement period* in respect of the 2011/12 inflation forecast error.

5.6 Transmission system price control – period of application

Despite section 1.3.1 of this access arrangement the transmission system price control commences on 1 July 2017. This price control applies annually on a financial year basis for the duration of the access arrangement period.

5.65.7 Transmission system revenue capprice control for revenue target cap services – years ending 30 June 2018 and 30 June 2019

- 5.6.15.7.1 The transmission system revenue price control cap for revenue cap target services is used to determine the maximum transmission revenue target cap service revenue (MMTRt) for Western Power's transmission system for each financial year t, where t is financial years ending 30 June 2018 and 30 June 2019.
- 5.6.2 The operation of the correction factor, TK_t, as described in sections 5.6.7 and 5.6.8 of this access arrangement will ensure that the MTR in financial year t is adjusted for any shortfall or over-recovery of actual transmission *revenue cap service* revenue compared to the MTR in preceding years.
- 5.6.3 For the purposes of this *transmission system* revenue cap for *revenue cap services*, Western Power's actual *transmission system* revenue in financial year t is transmission revenue earned in relation to the provision of *revenue cap services* in financial year t, subject to section 5.6.4 of this access arrangement. Where a revenue cap service is provided jointly by Western Power's *transmission system* and *distribution system*, the revenue earned must be allocated between the systems in a fair and reasonable manner.



- 5.6.4 Revenue received by Western Power for *excluded services, non-revenue cap services* and *capital contributions* will not be treated as actual revenue for the purposes of this *transmission system* revenue cap for *revenue cap services*.
- 5.6.5 Despite section 1.3.1 of this access arrangement the transmission system revenue cap for revenue cap services commences on 1 July 20122017. This revenue cap applies annually on a financial year basis for the duration of this access arrangement.
- 5.6.65.7.2 For th<u>e financial years ending 30 June 2018 and 2019</u> is access arrangement period, the maximum transmission revenue cap service revenue MMTR_t is determined as follows:

$$\mathbf{M}\underline{\mathbf{M}}\mathbf{T}\mathbf{R}_{t} = \mathbf{T}\mathbf{R}_{t} + \underline{\mathbf{T}\mathbf{K}_{t}} + \underline{\mathbf{T}\mathbf{A}\mathbf{A}\mathbf{3}_{t}} + \underline{\mathbf{T}\mathbf{K}_{t}} + \underline{\mathbf{T}\mathbf{K}_{t}}$$

where:

TR_t is the dollar amount for the financial year t calculated from the dollar amounts (expressed in 30 June 20122017 prices) set out in <u>Table 50 the table</u> below. For the avoidance of doubt, the dollar amounts set out in the table below include the amounts due to the recovery of *initial*-deferred revenue detailed in section 5.5.5 of this access arrangement for the transmission system. Note that the values in the table will be updated, and these values will be reported in the price list information for the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, as a result of the annual updates to weighted average cost of capital specified in section 5.4.

TK_{2017/18} = \$1.226M real as at 30 June 2017

TK_{2018/19} = \$0

 $TAA3_t$ is a positive or negative amount for the financial year t calculated to correct for any errors in the amounts included in the calculation of TR_t to give effect to the following adjustments (if applicable) arising from the operation of the previous *access arrangement*:

- Adjusting target revenue for unforeseen events;
- Adjusting target revenue for technical rule changes;
- Investment adjustment mechanism;
- Gain sharing mechanism;
- Service standards adjustment mechanism; and
- D_-factor <u>scheme</u>.

TAA3_t must take account of inflation, the time value of money and estimates (if any) of the above adjustments that have been included in the calculation of TR_t in this section 5.7.2 of this *access arrangement*. Western Power will provide model outputs to the *Authority* to demonstrate that the above adjustments have been made in accordance with the previous *access arrangement*.



5.8 Transmission system price control for revenue target services – years ending 30 June 2020, 30 June 2021 and 30 June 2022

- 5.8.1 The transmission system price control for revenue target services is used to determine the maximum transmission revenue target ("**TTR**_t") for Western Power's transmission system for each financial year t, where t is financial years ending 30 June 2020, 30 June 2021 and 30 June 2022.
- 5.8.2 For the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, TTR_t is determined as follows:

 $TTR_t = TR_t + TAA3_t$

where:

TR_t is as defined in section 5.7.2.

TAA3_t is as defined in section 5.7.2.

 Table 5.930: Transmission revenue captarget service revenues to be used for calculating TRt (\$ million real as at 30 June 20122017)

Table 50: Transmission revenue target service revenues to be used for calculating TRt (\$ million real as at 30 June 2017)

Financial year ending:	30 June	30 June	30 June	30 June	30 June
	2013 2018	201 4 <u>2019</u>	2015<u>2020</u>	2016<u>2021</u>	2017<u>2022</u>
TRt	<u>280.7283.0</u>	<u>282.1302.7</u>	<u>340.0348.6</u>	<u>407.7384.0</u>	<u>486.9421.4</u>
	287387.3	312328.1	337321.4	362290.6	387262.8

TAA2_L**TAA3**_L is a positive or negative amount for the financial year t calculated to correct for any errors in the amounts included in the calculation of TR_L to give effect to the following adjustments (if applicable) arising from the operation of the previous access arrangement:

- Adjusting target revenue for unforeseen events;
- Adjusting target revenue for technical rule changes;
- Investment adjustment mechanism;
- Gain sharing mechanism;
- Service standards adjustment mechanism; and
- D-factor.

TAA2_tTAA3_t must take account of inflation, the time value of money and estimates (if any) of the above adjustments that have been included in the calculation of TR_t in this section 5.6.6 of this *access arrangement*. Western Power will provide model outputs to the *Authority* to demonstrate that the above adjustments have been made in accordance with the previous *access arrangement*.

TK₄ is the correction factor calculated in accordance with sections 5.6.7 and 5.6.8 of this access arrangement. [wT1]



For the purpose of calculating TR_t , TK_t and therefore MTR_t and $\mp TTR_t$, in each financial year *CPI* adjustments will be effected by using published *CPI* data relating to the most recent December quarter compared to the December quarter in the previous year, with the exception of the financial year ending 30 June 2020 pricing year which will use the most recent September quarter compared to the September quarter in the previous year for the *CPI* to apply to financial year ending 30 June 2020 only.

5.8.3 Notwithstanding section 5.8.2 for the financial year ending 30 June 2021, TTR_t will also include an additional term TK' as follows:

 $\underline{\mathsf{TK'}} = (\mathsf{AMTR}_{2018/19} - \mathsf{FMTR}_{2018/19}) * (1 + \mathsf{WACC}_{2018/19}) * (1 + \mathsf{WACC}_{2019/20})$

where:

AMTR_{2018/19} is the actual transmission revenue received in 2018/19.

FMTR_{2018/19} = \$291.711M nominal

WACC_{2018/19} is as defined in section 5.4.

WACC_{2019/20} is as defined in section 5.4.

5.9 Distribution system price control – period of application

5.9.1 Despite section 1.3.1 of this access arrangement the distribution system price control commences on 1 July 2017. This price control applies annually on a financial year basis for the duration of the access arrangement period.

5.6.7 For the financial year ending on 30 June 20132018:

 $\begin{array}{l} \mathsf{TK}_{2012/13} = (\mathsf{FTR}_{2010/11} - \mathsf{ATR}_{2010/11} \frac{\mathsf{TK}_{2017/18} = (\mathsf{FTR}_{2015/16} - \mathsf{ATR}_{2015/16}) * (1 + \\ & 7.98\underline{3.60}\%) * (1 + \mathsf{WACC}_{\mathsf{post tax real}}) + (\mathsf{MTR}_{2011/1} - \mathsf{FTR}_{2011/12} \frac{\mathsf{WACC}_{2017/18}) + \\ & (\underline{\mathsf{MTR}_{2016/17} - \mathsf{FTR}_{2016/12}) * (1 + \mathsf{WACC}_{\mathsf{post tax real}} \frac{\mathsf{WACC}_{2017/18})}{\mathsf{WACC}_{2017/18})} \end{array}$

For financial years ending on 30 June 20142019 to 30 June 20172022:

```
TK_{t} = (FTR_{t-2} - ATR_{t-2})^{*} (1 + WACC_{post-tax real})^{2} \frac{WACC_{t})^{*} (1 + WACC_{t-1})^{*} + (MTR_{t-1} - FTR_{t-1})^{*} \frac{(1 + WACC_{post-tax real})^{2} WACC_{t}}{(1 + WACC_{post-tax real})^{2} WACC_{t}}
```

where:

FTR_{2010/11} FTR_{2015/16} is \$355.6328.8 million (real as at 30 June 20122017)

ATR_{2010/11}ATR_{2015/16} is \$356.1<u>324.3</u> million (real as at 30 June 2012<u>2017)</u>

MTR_{2011/12} MTR_{2016/17} is \$414263.1 million (real as at 30 June 20122017)

FTR_{2011/12} FTR_{2016/17} is \$387.9293.6 million (real as at 30 June 20122017)

FTR_{t-2} is the forecast transmission *revenue cap services* revenue in the financial year t-2 as calculated in the financial year t-2.

ATR₁₂ is the actual transmission *revenue cap services* revenue in the financial year t-2 as defined in accordance with section 5.6.3 of this access arrangement.

MTR_{L1} is the maximum *revenue cap services* revenue for Western Power's *transmission system* in the financial year t-1.



FTR_{t1} is the forecast transmission *revenue cap services* revenue in the financial year t-1.

WACC post tax real WACC 2017/18 is 4.3821% real post tax

WACC_{2018/19} is 4.38%²21% real post tax

WACC is the *weighted average cost of capital* in year t for the *Western Power Network* as detailed in section 5.4.1<u>5.4</u> of this *access arrangement*, on a post-tax real basis.

WACC_{L1} is the *weighted average cost of capital* in year t-1 for the *Western Power Network* as detailed in section 5.4 of this *access arrangement*, on a posttax real basis.

This formula reflects that the annual tariff-setting process for financial year t typically takes place before the end of financial year t-1. Therefore, TK_{t} will need to be estimated in the first instance, and then recalculated in the subsequent financial year when ATR_{t-2} is known.

5.6.8 The correction factor, TK_t, will also apply:

- a) in the first year of the next access arrangement period to adjust for any difference between maximum transmission revenue cap services revenue and forecast transmission revenue cap services revenue, in relation to the financial year ending on 30 June 2017<u>2022</u> and for any difference between forecast transmission revenue cap services revenue and actual transmission revenue cap services revenue, in relation to the financial year ending on 30 June 2016<u>2021</u>; and
- b) in the second year of the next access arrangement period to adjust for any difference between forecast transmission revenue cap services revenue and actual transmission revenue cap services revenue, in relation to the financial year ending on 30 June 2017<u>2022</u>.

5.10 Distribution system revenue capprice control for revenue captarget services – years ending 30 June 2018 and 30 June 2019

5.7____

- 5.7.15.10.1 The distribution system revenue capprice control for revenue target services is used to for revenue cap services is used to determine the maximum distribution the maximum distribution revenue cap target service revenue (MMDRt) for Western Power's distribution system for each financial year t, where t is financial year ending 30 June 2018 and 30 June 2019.
- 5.7.2 The operation of the correction factor, DK_t , as described in sections 5.7.7 and 5.7.8 of this *access arrangement* will ensure that the MDR in financial year t is adjusted for any

 $[\]frac{2}{2}$ This figure is a 'placeholder' will be updated as part of the *approval* of the proposed access arrangement by the Authority.



EDM 44531823 Page 47 shortfall or over-recovery of actual distribution *revenue cap service* revenue compared to the MDR in preceding years.

- 5.7.3 For the purposes of this *distribution system* revenue cap, Western Power's actual *distribution system* revenue in financial year t is distribution revenue earned in relation to the provision of *revenue cap services* in financial year t, subject to section 5.7.4 of this *access arrangement*. Where a *revenue cap service* is provided jointly by Western Power's *transmission system* and *distribution system*, the revenue earned must be allocated between the systems in a fair and reasonable manner.
- 5.7.4 Revenue received by Western Power for *excluded services, non-revenue cap services* and *capital contributions* will not be treated as actual revenue for the purposes of this *distribution system* revenue cap for *revenue cap services*.
- 5.7.5 Despite section 1.3.1 of this *access arrangement* the *distribution system* revenue cap for *revenue cap services* commences on 1 July 20122017. This revenue cap applies annually on a financial year basis for the duration of this *access arrangement*.
- 5.7.65.10.2 For the financial years ending 30 June 2018 and 30 June 2019, MDRt is defined as follows this access arrangement period, the maximum regulated distribution revenue MDRt is determined as follows:

$$\mathbf{M}\underline{\mathbf{M}}\mathbf{D}\mathbf{R}_{t} = \mathbf{D}\mathbf{R}_{t} + \underline{\mathbf{D}}\underline{\mathbf{K}}_{t} + \underline{\mathbf{T}}\mathbf{E}\mathbf{C}_{t} + \underline{\mathbf{D}}\underline{\mathbf{A}}\underline{\mathbf{A}}_{t} + \underline{\mathbf{D}}\underline{\mathbf{K}}_{t}$$

where:

DR_t is the dollar amount for the financial year t calculated from the dollar amounts (expressed in 30 June 20122017 prices) set out in the Table 51. For the avoidance of doubt, the dollar amounts set out in the table below include the amounts due to the recovery of *initial-deferred revenue* and *additional transmission_deferred revenue* detailed in section 5.5.5 of this *access arrangement* for the *distribution system*. Note that the values in the table will be updated, and these values will be reported in the *price list information* for the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, as a result of the annual updates to *weighted average cost of capital* specified in section 5.4.

Table 5.1031: Distribution revenue cap service revenues to be used for calculating DR_± (\$ million real as at 30 June 20127)

Table 51: Distribution revenue cap service revenues to be used for calculating DRt (\$ million real as at 30 June 2017)

Financial year ending:	30 June	30 June	30 June	30 June	30 June
	2013 2018	201 4 <u>2019</u>	2015<u>2020</u>	2016<u>2021</u>	2017<u>2022</u>
DRt	<u>991.5993.0</u>	<u>1,001.4</u> 684.8	<u>974.51,050.8</u>	<u>926.81,051.2</u>	<u>875.8-1,046.2</u>
	685 <u>1,000</u> .7	<u>1,059.3</u> 983.6	816.7 <u>1,091.5</u>	932.9 <u>1,108.5</u>	1,120018.0

DK_{2017/18} = \$36.407M real as at 30 June 2017

DK_{2008/19} = \$0



 TEC_t is any cost incurred by the *distribution system* for the financial year t as a result of the tariff equalisation contribution in accordance with section 6.37A of the *Code*.

DAA2 DAA3 is a positive or negative amount for the financial year t calculated to correct for any errors in the amounts included in the calculation of DR_t to give effect to the following adjustments (if applicable) arising from the operation of the previous access arrangement:

- Adjusting target revenue for unforeseen events;
- Adjusting target revenue for technical rule changes;
- Investment adjustment mechanism;
- Gain sharing mechanism;
- Service standards adjustment mechanism; and
- D-_factor_scheme.

 $\frac{DAA2_{t}DAA3_{t}}{DAA3_{t}}$ must take account of inflation, the time value of money and estimates (if any) of the above adjustments that have been included in the calculation of DR_t in this section 5.10.2-of this access arrangement. Western Power will provide model outputs to the Authority to demonstrate that the above adjustments have been made in accordance with the previous access arrangement.

5.11 Distribution system price control for revenue target services – years ending 30 June 2020, 30 June 2021 and 30 June 2022

- 5.11.1 The distribution system price control for revenue target services is used to determine the maximum distribution revenue target (TDR_t) for Western Power's distribution system for each financial year t, where t is financial year ending 30 June 2020, 30 June 2021 and 30 June 2022.
- 5.11.2 For the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, DTR_t is determined as follows:

DTR $_t = DR_t + TEC_t + DAA3_t + DTEC_t$

where:

DR_t is as defined in section 5.10.2.

 $\underline{\text{TEC}_{t} \text{ is as defined in section } 5.10.2.}$

DAA3_t is as defined in section 5.10.2.

DTEC_t is an adjustment for any shortfall or over-recovery of actual *distribution system revenue* compared to TEC_t in preceding years and is calculated in accordance with section 5.11.3 of this access arrangement.



DK_t is the correction factor calculated in accordance with sections 5.7.7 and 5.7.8 of this access arrangement.

For the purpose of calculating DR_t , $DK_t DK_t$ -and therefore $MMDR_t$ and DTR_t , in each financial year *CPI* adjustments will be effected by using published *CPI* data relating to the most recent December quarter compared to the December quarter in the previous year., with the exception of the financial year ending 30 June 2020 pricing year which will use the most recent September quarter compared to the September quarter in the previous year for the *CPI* to apply to financial year ending 30 June 2020 only.

5.7.7<u>5.11.3</u> For the financial year ending on 30 June 2013201820 to 30 June 2022:

 $\frac{\text{DTEC}_{t} = (\text{ATEC}_{t-2} - \text{FTEC}_{t-2}) * (1 + \text{WACC}_{t}) * (1 + \text{WACC}_{t-1}) + (\text{TEC}_{t-1} - \text{FTEC}_{t-2}) * (1 + \text{WACC}_{t})}{\text{WACC}_{t}}$

where:

ATEC_t is the actual tariff equalisation contribution revenue received in financial year t.

FTECt is the forecast of tariff equalisation contribution revenue to be received in financial year t.

TEC_t is the amount of tariff equalisation contribution to be recovered in a financial year t as gazetted.

WACC_t is the *weighted average cost of capital* in year t-1 for the *Western Power Network* as detailed in section 5.4 of this *access arrangement*, on a post-tax real basis.

5.11.4 Notwithstanding clause 5.11.2 for the financial year ending 30 June 2021, DTR_t will also include an additional term DK' as follows:

 $\underline{DK' = (AMDR_{2018/19} - FMDR_{2018/19}) * (1 + WACC_{2018/19}) * (1 + WACC_{2019/20})}$

where:

AMDR_{2018/19} is the actual revenue received in 2018/19

FMDR_{2018/19} = \$1,218.981M nominal

WACC_{2018/19} is as defined in section 5.4

WACC2019/20 is as defined in section 5.4

 $\begin{array}{l} \mathsf{DK}_{2012/13} = \left(\mathsf{FDR}_{2010/11} - \mathsf{ADR}_{2010/11} \mathsf{DK}_{2017/18} = \left(\mathsf{FDR}_{2015/16} - \mathsf{ADR}_{2015/16}\right)^{*} \\ & \left(1+7.98\underline{3.60}\%\right)^{*} \left(1+\mathsf{WACC}_{\mathsf{post-tax-real}}\right) + \left(\mathsf{MDR}_{2011/12} - \mathsf{FDR}_{2011/12} \mathsf{WACC}_{2017/18}\right) + \\ & \left(\mathsf{MDR}_{2016/17} - \mathsf{FDR}_{2016/17}\right)^{*} \left(1+\mathsf{WACC}_{\mathsf{post-tax-real}} \mathsf{WACC}_{2017/18}\right) \end{array}$

For financial years ending on 30 June 20142019 to 30 June 20172022:

 $\frac{\mathsf{DK}_{t} = (\mathsf{FDR}_{t-2} - \mathsf{ADR}_{t-2}) * (1 + \mathsf{WACC}_{\mathsf{post-tax-real}})^2 \cdot \frac{\mathsf{WACC}_{t} * (1 + \mathsf{WACC}_{t-1}) + (\mathsf{MDR}_{t-1} - \mathsf{FDR}_{t-1})}{1 + \mathsf{WACC}_{\mathsf{post-tax-real}} \cdot \frac{\mathsf{WACC}_{t}}{\mathsf{WACC}_{t}}}$

FDR_{2010/11}where:

FDR_{2015/16} is \$729.9<u>1,191.1</u> million (real as at 30 June 2012<u>2017</u>)



ADR_{2010/11}ADR_{2015/16} is \$733.31,173.6 million (real as at 30 June 20122017)

MDR_{2011/12}MDR_{2016/17} is \$855.91,120.2 million (real as at 30 June 20122017)

FDR_{2011/12}FDR_{2016/17} is \$804.81,218.0 million (real as at 30 June 20122017)

FDR_{t-2} is the forecast distribution *revenue cap services* revenue in the financial year t-2 as calculated in the financial year t-2.

ADR₁₋₂ is the actual *revenue cap service* distribution revenue in the financial year t-2 as defined in accordance with section 5.7.3 of this *access arrangement*.

MDR_{t1} is the maximum *revenue cap service* revenue for Western Power's *distribution system* in the financial year t-1.

FDR_{L1} is the forecast distribution *revenue cap services* revenue in the financial year t-1.

WACCpost tax real WACC2017/18 is 4.3821% real post tax.

WACC_{2018/19} is 4.38%³21% real post tax.

WACC is the weighted average cost of capital for year t for the Western Power Network as detailed in section 5.4.1<u>5.4</u> of this access arrangement on a post tax real basis.

WACC.1 is the weighted average cost of capital in year t 1 for the Western Power Network as detailed in section 5.4 of this access arrangement, on a posttax real basis.

This formula reflects that the annual tariff setting process for financial year t typically takes place before the end of financial year t-1. Therefore, DK_t will need to be estimated in the first instance, and then recalculated in the subsequent financial year when ADR_{t-2} is known.

5.7.8 The correction factor, DK_t, will also apply:

- a) in the first year of the next access arrangement period to adjust for any difference between maximum distribution revenue cap services revenue and forecast distribution revenue cap services revenue, in relation to the financial year ending on 30 June 2017<u>2022</u> and for any difference between forecast distribution revenue cap services revenue and actual distribution revenue cap services revenue, in relation to the financial year ending on 30 June 2016<u>2021</u>; and
- b) in the second year of the next access arrangement period to adjust for any difference between forecast distribution revenue cap services revenue and actual distribution revenue cap services revenue, in relation to the financial year ending on 30 June 20172022.

³<u>This figure is a 'placeholder' will be updated as part of the *approval* of the proposed access arrangement by the Authority.</u>



6 Pricing methods, price lists and price information

6.1 Purpose

6.1.1 Pursuant to section 5.1(e) and chapter 7 of the *Code*, this section describes the *pricing methods* applied by Western Power.

6.2 Network pricing objectives

- 6.2.1 Western Power's *pricing methods* are designed to achieve the objectives set out in sections 7.3 and 7.4 of the *Code*.
- 6.2.2 In accordance with the objectives set out in sections 7.3 and 7.4 of the *Code*, Western Power's *pricing methods* seeks to recover the costs of providing *reference services* from *users* in a manner that is simple, practical and equitable.

6.3 Overview of pricing methods

- 6.3.1 *Reference tariffs* are derived from an analysis of the cost of *reference service* provision which entails:
 - a) identifying the costs of providing *revenue captarget services*;
 - b) determining the expected *non-reference service* revenue within the costs of providing *revenue* captarget services;
 - c) deducting the expected *non-reference service* revenue from the costs of providing *revenue* captarget services to determine the costs of providing *reference services*;
 - d) allocating the costs of providing *reference services* to particular *reference service* customer groups;
 - e) translating the costs of serving particular *reference service* customer groups to the costs of providing *reference tariffs*; and
 - f) determining a structure of *reference tariffs* in a manner that reflects the underlying cost structure, in accordance with section 7.6 of the *Code*.
- 6.3.2 The costs relating to *reference services* A1 to A10-and, A12 to A17 and C1 to C4815 and D1 toand D42 are allocated so that these costs can determine the relevant *reference tariff* in a cost reflective manner.
- 6.3.3 *Reference tariffs* for *reference services* A11, B1 and to B23 are location-specific and are published for each electrical node.



6.4 Price list and price list information

- 6.4.1 The price lists in respect of the pricing year ending on 30 June 20132018 and the pricing year ending on the day before the effective date under date in section 1.3.1 of this access arragenemtarrangement (30 June 2019) is are attached at Appendix 0.F.1 and F.3 respectively. In respect of these pricing years, these are ending on 30 June 2018 and the pricing year ending on the day before the date in section 1.3.1 of this access arrangement, this is the current price lists for the purposes of section 5.1(f) of the Code. The respective price list information for this epice lists is are attached at Appendix 0.F.2 and F.4.—
- 6.4.2 The price list is to be updated in accordance with Chapter 8respect of the Code. The pricing yearsyear commencing on the date in section 1.3.1 of this access arrangement (1 July 2019) and ending on 30 June 201209 is attached at Appendix F.35. The price list information for this access arrangement period are defined in the table below: price list is attached at Appendix F.46.

<u>1.1.1 Pricing</u> year	<u>1.1.1</u> Start date	<u>1.1.1</u> End date
1	Effective date under section 1.3.1 of this access arrangement	
2		
3	<u> </u>	
4	<u> </u>	
5	<u> </u>	

1.1.1.— Table 30: Pricing years for this access arrangement period

6.4.3 In accordance with section 8.1 of the *Code* this *access arrangement* requires Western Power to submit a proposed *price list*, together with *price list information*, to the *Authority* for approval at least 45 *business days* before the start of <u>the *pricing year* ending</u> <u>30 June 20201 and each *pricing year* (exceptthereafter30 June 2022.</u>



6.4.4 The pricing years for thise access arrangement period are defined in the table below:

Table 52: Pricing years for this access arrangement period								
Pricing year	Start date	End date						
<u>1</u>	<u>1 July 2017</u>	<u>30 June 2018</u>						
<u>2</u>	<u>1 July 2018</u>	The day before the effective date under section 1.3.1 of this access arrangement (30 June 2019)						
<u>33</u>	Effective date under section 1.3.1 of this access arrangement (1 July 2019)Effective date under section 1.3.1 of this access arrangement	<u>30 June 202030 June 2019</u>						
<u>44</u>	<u>1 July 20201 July 2019</u>	<u>30 June 202130 June 2020</u>						
<u>55</u>	<u>1 July 20211 July 2020 1</u>	<u>30 June 202230 June 2021</u>						
<u>6</u>	<u>1 July 2021</u>	30 June 2022						

Table 6.132: Pricing years for this access arrangement period Table 52: Pricing years for this access arrangement period

6.4.5 For the purposes of the price list and price list information in the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, Western Power will use the customer information in the table below to determine prices:



Table 6.2: Customer numbers and energy volumes

Customer	<u>Sub-</u>	<u>Tariffs</u>	<u>2019</u>)/20	<u>2020</u>	<u>)/21</u>	<u>2021/22</u>	
<u>segment</u>	<u>segment</u>		<u>Customer</u> <u>numbers</u>	<u>Energy</u> <u>volumes,</u> <u>GWh</u>	<u>Customer</u> <u>numbers</u>	<u>Energy</u> <u>volumes,</u> <u>GWh</u>	<u>Customer</u> <u>numbers</u>	<u>Energy</u> volumes, <u>GWh</u>
<u>Residential</u>	<u>Without</u> <u>PV</u>	<u>RT1,</u> <u>RT3,</u> <u>RT17,</u> <u>RT19,</u> <u>RT21</u>	<u>810,777</u>	<u>4,088</u>	<u>810,556</u>	<u>3,996</u>	<u>810,672</u>	<u>3,911</u>
	With PV	<u>RT13,</u> <u>RT15</u>	<u>254,837</u>	<u>1,103</u>	<u>275,034</u>	<u>1,080</u>	<u>294,895</u>	<u>1,054</u>
Unmetered s	upply	<u>RT10</u>		<u>16,493</u>	<u>40</u>	<u>16,641</u>	<u>41</u>	<u>16,789</u>
<u>Small</u> <u>businesses</u>	<u>Without</u> <u>PV</u>	<u>RT2,</u> <u>RT4,</u> <u>RT18,</u> <u>RT20,</u> <u>RT22</u>	<u>81,740</u>	<u>1,759</u>	<u>80,886</u>	<u>1,654</u>	<u>80,008</u>	<u>1,554</u>
	With PV	<u>RT14,</u> <u>RT16</u>	<u>2,250</u>	<u>284</u>	<u>2,420</u>	<u>345</u>	<u>2,590</u>	<u>406</u>
<u>Medium</u> <u>businesses</u>	<u>Low</u> <u>voltage</u> <u>business</u>	<u>RT6</u>	<u>3,967</u>	<u>2,037</u>	<u>3,998</u>	<u>1,964</u>	<u>4,029</u>	<u>1,948</u>
	<u>High</u> <u>voltage</u> <u>business</u>	<u>RT5</u>	<u>296</u>	<u>758</u>	<u>300</u>	<u>803</u>	<u>303</u>	<u>835</u>
<u>Large</u> businesses	<u>Low</u> <u>voltage</u> <u>business</u>	<u>RT8</u>	<u>58</u>	<u>186</u>	<u>58</u>	<u>181</u>	<u>58</u>	<u>176</u>
	<u>High</u> <u>voltage</u> <u>business</u>	<u>RT7</u>	<u>291</u>	<u>3,109</u>	<u>293</u>	<u>3,068</u>	<u>295</u>	<u>3,012</u>
Streetlights		<u>RT9</u>		288,415	<u>141</u>	296,223	<u>143</u>	304,058

Table 53: Customer numbers and energy volumes

the first pricing year).

6.5 Pricing methods

6.5.1 This section of the *access arrangement* explains how the *pricing methods* comply with sections 7.3 and 7.4 of th<u>e</u> *Code*. In accordance with the *Code* requirements, the *price list information* provided as Appendix <u>0F.46</u> to this<u>e</u> *access arrangement* explains the *pricing methods* that underpinned the development of *reference tariffs* for this *access arrangement period*.



Revised proposed revisions to the Access Arrangement for the Western Power Network



Recovery of forward-looking efficient costs of providing reference services

- 6.5.2 In accordance with section 7.3(a) of the *Code, reference tariffs* are designed to recover the forward-looking efficient costs of providing *reference services*. Further information is provided in the *price list information*, Appendix <u>9F.46</u> to th<u>ise</u> access arrangement.
- 6.5.3 Western Power, as a *reasonable and prudent person*, will set the *reference tariffs* in the *price list* so that the forecast *transmission system* revenue for *revenue <u>captarget</u>* services for year t <u>recovers MTR or TTR as applicable</u> <u>does not exceed MTR</u>_t-and the forecast *distribution system* revenue for *revenue <u>cap-target</u>* services for year t <u>does not exceed MDR_t-and the forecast <u>MDR</u>_t-and the forecast <u>MDR</u>_t-and the forecast <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the forecast <u>services</u> for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and the services for year t <u>does not exceed</u> <u>MDR</u>_t-and t <u>services</u> <u>for year</u> <u>transmission</u> <u>services</u> <u>for year</u> <u>transmission</u> <u>services</u> <u>services</sub> <u>services</u> <u>services</u> <u>services <u>services</u> <u>services</sub> <u>services</u> <u>services <u>ser</u></u></u></u></u></u>
- 6.5.4 *Non-revenue* captarget services revenue is recovered on a fee-for-service basis.
- 6.5.5 *Capital contributions* are charged in accordance with Western Power's *contributions policy*. In general terms, such *contributions* seek to recover in net present value terms any shortfall between the expected revenue from *reference tariffs* and the costs of connection.

Reference tariffs should be between the *incremental* and the *stand-alone cost of service provision*.

6.5.6 In accordance with section 7.3(b)(i) and (ii) of the *Code, reference tariffs* are set to at least recover the *incremental cost of service provision*, but to be less than the *stand-alone cost of service provision*. Further information is provided in the *price list information*, Appendix F.2 F.46 to thise access arrangement.

Charges paid by different users of a reference service

- 6.5.7 In accordance with section 7.4(a) of the *Code*, the *charges* paid by different *users* of a *reference serv*ice differ only to the extent necessary to reflect differences in the *average cost of service provision* to the *users*.
- 6.5.8 Each of the *reference tariffs* takes into account the metering information available for each *reference service*, and therefore contains components that vary with usage or demand. In addition *reference tariffs* for *reference services* A5, A6, A7, A8, <u>C5, C6, C7, C8</u>, A11, B1 and B2 vary with location. Within the requirements of section 7.4(a) and 7.7 of the *Code*, these components reflect the differences in the average cost of different *users* of the same *reference service*. Further information is provided in the *price list information*, Appendix F.2 F.46 to thise access arrangement.

Reasonable requirements of *users*

6.5.9 In accordance with section 7.4(b) of the *Code*, the structure of *reference tariffs* has been set to reasonably accommodate the requirements of *users* collectively. This has been



EDM 44531823 Page 57 achieved by developing the *reference tariffs* through a consultative process that involved Government and industry stakeholders.

Structure of tariffs should enable a user to predict likely annual changes

6.5.10 In accordance with section 7.4(c) of the *Code, users* can predict the likely annual changes in *reference tariffs*. All *reference tariffs* are specified for<u>until</u> the firstfinancial year of the access arrangementending 30 June 201920. For the remainder of this access arrangement period rebalancing of *reference tariffs* is constrained by the imposition of side constraints on annual revenue movements. In addition, the *revenue caps targets* have been smoothed across this access arrangement period to facilitate smooth price movements.

Avoidance of price shock

- 6.5.11 The *transmission system* and *distribution system* <u>target</u> revenue caps for revenue cap <u>target</u> services haves each been smoothed across this access arrangement period so that price movements will be smoothed from year to year.
- 6.5.12 In accordance with section 7.4(d) of the *Code*, rebalancing of *reference tariffs* is constrained by the imposition of side constraints on annual revenue movements.
- 6.5.13 To constrain *reference tariff* rebalancing the maximum change in *reference tariff* revenue for the *transmission system* from each *reference tariff* when the *price list* is updated is:

-For the financial year ending on 30 June 2013:

$$\frac{\sum_{y=1}^{n} p_{2012/13}^{xy} q_{2012/13}^{xy}}{\sum_{y=1}^{n} p_{2011/12}^{xy} q_{2012/13}^{xy}} \leq (1 + CPI_{2012/13})(1 - TX_{2012/13}) + B'_{2012/13} + 0.02$$

---For financial years ending on 30 June 20142019 to 30 June 202020172020:

$$\frac{\sum_{y=1}^{n} p_{t}^{xy} q_{t}^{xy}}{\sum_{y=1}^{n} p_{t-1}^{xy} q_{t}^{xy}} \leq (1 + CPI_{t})(1 - TX_{t}) + B'_{t} + 0.02$$

where:



-t is the financial year in which the reference tariffs as varied will apply;

-t-1 is the financial year immediately preceding financial year t;

 $-\frac{p_{t-1}^{xy}}{2012}p_{t-1}^{xy}$ is the price being charged in the financial year ending on 30 June $\frac{p_{t-1}^{xy}}{2012}t - 1$ -for component-*y*-of a given *reference tariff x*;

 $-\frac{p_t^{xy}}{p_{2012/13}^{xy}} \frac{p_t^{xy}}{p_t^{2012/13}} \xrightarrow{p_t^{xy}}$ is the average of the <u>proposed</u> price being charged between 1 July $\frac{2012 - 31}{2012 - 31}$ January 2013 and the price charged between 1 February 2013 - 30 June 2013 for component *y* of a given *reference tariff x x x* <u>in financial year</u> *t*;

 $-\frac{q_t^{xy}}{q_{2012/13}^{xy}} q_t^{xy} - \frac{q_t^{xy}}{q_t^{xy}} - \frac{q_t^{xy}$

 $---q_t^{xy}$ -is the quantity of component-y-of a given reference tariff x that is forecast to be sold in financial year t;

_*CPI*_____is 2.25%;

*TX*_{2012/13}<u>is 6.7%;</u>

 $-\frac{TX_{t}}{T}$ is the annual percentage change in $\frac{TR_{t}}{T}$ and is <u>initially</u> determined to be:

<u>Table 33: TXt</u>





<u>_____is 6.8%;</u>

<u>Financial</u> year ending:		
<u> </u>		



EDM 44531823 Page 60 $-\frac{B'_{t}}{B'_{t}}$ -is the annual correction factor in financial year *t*-determined as follows:

$$B_{t}^{\prime} = \frac{TK_{t} + TAA3_{t}}{TR'_{t}}$$

 $--\frac{TK_t}{T}$ is as defined in section 5.6.6 of this access arrangement;

-TAA3, ________ is as defined in section 5.6.6 of this access arrangement;

The values for TX_t in table Table <u>30 will be updated</u>, and these values will be reported in the price list information for the financial years ending <u>30 June 2020</u>, <u>30 June 2021</u> and <u>30 June 2022</u>, as a result of the annual updates to weighted average costs of capital specified in section 5.4.

6.5.14<u>6.5.13</u> To constrain *tariff* rebalancing the maximum change in *reference tariff* revenue for the *distribution system* from each *reference tariff* when the *price list* is updated is:

For the financial year ending on 30 June 2013:

$$\sum_{y=1}^{n} p_{2012/13}^{xy} q_{2012/13}^{xy} \leq (1 + CPI_{2012/13})(1 - DX_{2012/13}) + A'_{2012/13} + 0.02$$

$$\sum_{y=1}^{n} p_{2011/12}^{xy} q_{2012/13}^{xy}$$

For financial years ending on 30 June 2014 2019 to 30 June 2017 2022:

$$\frac{\sum_{y=1}^{n} p_{t}^{xy} q_{t}^{xy}}{\sum_{y=1}^{n} p_{t-1}^{xy} q_{t}^{xy}} \leq (1 + CPI_{t})(1 - X_{t}) + A'_{t} + 0.02$$

$$\frac{\sum_{y=1}^{n} p_{t-1}^{xy} q_{t}^{xy}}{\sum_{y=1}^{n} p_{t-1}^{xy} q_{t}^{xy}} \leq (1 + CPI_{t})(1 - DX_{t}) + A'_{t} + 0.02$$

where:



a given *reference tariff* x, has up to n tariff components, and where:

- *t* is the financial year in which the *reference tariffs* as varied will apply;
- t-1 is the financial year immediately preceding financial year t;
- p_{t-1}^{xy} is the price being charged in the financial year t-1 for component y of a given *reference tariff* x;
- p_t^{xy} is the proposed price for component y of a given *reference tariff* x in financial year t;
- $\frac{q_t^{xy}}{p_{2011/12}^{2011/12}} \xrightarrow{\text{is the price being charged in the financial year ending on 30}}{\text{June 2012 for component-}y of a given reference tariff x;}$
- $p_{2012/13}^{xy}$ is the average of the price being charged between 1 July 2012 31 January 2013 and the price charged between 1 February 2013 – 30 June 2013 for component -y of a given *reference tariff x*;
- p_{t-1}^{xy} is the price being charged in the financial year t-1 for component y of a given reference tariff x;
- p_t^{xy} is the proposed price for component *y* of a given *reference tariff x* in financial year *t*;

 $q_{2012/13}^{xy} q_t^{xy}$ is the quantity of component y of a given *reference tariff* x that is forecast to be sold in financial year t ending on 30 June 2013; t;

- *CPI*_t is the percentage increase in the *CPI* data relating to the most recent December quarter compared to the December quarter in the previous year;
 - $X_t = q_t^{xy}$ is the quantity of component y of a given *reference tariff* x that is forecast to be sold in financial year t;

*CPI*_{2012/13} is 2.25%;

-DX 2012/13 is 1.9%

 DX_{i} is the annual percentage change in <u>the sum of $DR_{i}DR_{t}$ and <u>TR_t</u> is <u>initially</u> determined to be:</u>



Table 6.334: DX₄

	Tab	le	54:	Xt
--	-----	----	-----	----

Financial year ending:	30 June	30 June	30 June	30 June
	201 4 <u>2019</u>	2015<u>2020</u>	2016<u>2021</u>	2017<u>2022</u>
₽Xt	<u>0.51%-</u>	<u>-3.85%-</u>	<u>-1.52%-</u>	<u>-</u>
	<u>0.84%-</u>	<u>4.93%-</u>	<u>0.04%3-</u>	2.12% 0.48
	51.9 <u>5.86</u> %	31.2 <u>3.04</u> %	<u>1.55</u> %	<u>%8-1.05</u> %

<u>A'_{2012/13} is 3.3%;</u>

 A'_t is the annual correction factor in financial year t determined as follows:follows:

 $\underline{A'_{t}} = (\underline{DAA3_{t}} + \underline{TAA3_{t}} + \underline{\triangle}\underline{TEC_{t}} + \underline{DTEC_{t}})$ $(\underline{DR'_{t}} + \underline{TR'_{t}})$

$$A_{t}' = \frac{DK_{t} + DAA3_{t} + \Delta TEC_{t}}{DR'_{t}}$$

 DK_t is as defined in section 5.10.2 of thise access arrangement;

 $DAA3_t$ is as defined in section 5.10.2 of thise access arrangement;

- ΔTEC_t is the difference in the cost incurred by the *distribution system* between the financial years t-1 and t as a result of the tariff equalisation contribution in accordance with section 6.37A of the *Code*;
- DTECtis the revenue correction factor for the tariff equalisation contributionas defined in section 5.11.3 of the access arrangement;
- DR'_{t} is DR_{t} (as set out in section 5.10.2 of thise access arrangement), converted to nominal dollars:
- $\frac{TR'_{t}}{converted to nominal dollars.}$
- 6.5.14 The values for ĐX_t in will be updated and these values will be reported in the price list information for the financial years ending 30 June 2020, 30 June 2021 and 30 June 2022, as a result of the annual updates to weighted average costs of capital specified in section 5.4. Note that the update for the financial year ending 30 June 2021 will update the weighted average cost of capital for 30 June 2020 and 30 June 2021.



Tariff components

6.5.15 In accordance with section 7.6 of the *Code, reference tariffs* have been designed so that the *incremental cost of service provision* is to be recovered by *tariff* components that vary with usage, and the costs in excess of the *incremental cost of service provision* are to be recovered through *tariff* components that do not vary with usage. Further information is provided in the *price list information*, Appendix F.2.F.46 to thise access arrangement.

6.6 Policy on prudent discounting

- 6.6.1 In accordance with section 7.9 of the *Code*, Western Power may discriminate between *users* in its pricing of *services* to the extent that it is necessary to do so to aid economic efficiency, by:
 - a) entering into an agreement with a *user* to apply a *discount* to the *equivalent tariff* to be paid by the *user* for a *covered service*; and
 - b) then, recovering the amount of the *discount* from other *users* of *reference services* through *reference tariffs*.
- 6.6.2 In exercising its discretion with regard to prudent discounting, Western Power will have regard to the pricing objectives in sections 7.3 and 7.4 of the *Code*.
- 6.6.3 Western Power may offer a prudent discount if the existing *user* or *applicant* seeking *access* to the *Western Power Network* is able to demonstrate that another supply option will provide a comparable *service* at a lower price than that offered by Western Power's *reference services* and *reference tariffs*.
- 6.6.4 The existing *user* or *applicant* must provide Western Power with sufficient details of the cost of the other option to enable Western Power to calculate the annualised cost of the other option.
- 6.6.5 Western Power's discounted price offer will be set to reflect the higher of:
 - a) the cost of the other option $\frac{1}{7}$ or
 - b) the incremental cost of service provision.

6.7 Policy on discounts for distributed generation

6.7.1 In accordance with section 7.10 of the *Code*, Western Power will offer will provide, through reference services B3 and C15, to a-users who connects distributed generating plant and other non-network solutions behind the connection point which provide benefits to the Western Power Network that defer its, a share of any reductions in either or both of Western Power's capital-related costs or non-capital costs which benefits arise as a result of the entry point or bi-directional point for distributed generating plantbeing



located in a particular part of the Western Power Network a discount as described and calculated under the Price List-by:

- a) entering into an agreement with a *user* to apply a *discount* to the *equivalent tariff* to be paid by the *user* for a *covered service*; and
- 6.7.2<u>6.7.1</u> then, recovering the amount of the *discount* from other *users* of *reference services* through *reference tariffs*.
- 6.7.3 The amount of the total *discount* available under section 6.7.1 of this access arrangement will be determined by Western Power as the forecast *capital-related costs* and *non-capital costs* that would be incurred if the *distributed generating plant* were not to *connect* minus the forecast *capital-related costs* and *non-capital costs* that would be incurred if the *distributed generating plant* were to *connect*. The cost analysis will be conducted over a period of at least 10 years, depending on the availability and accuracy of data. A *discount* will only be payable if the amount calculated in accordance with this section 6.7.2 of this *access arrangement* is greater than zero.
- 6.7.4 The discount calculated in accordance with section 6.7.2 of this access arrangement will be calculated in present value terms and, using the weighted average cost of capital for the Western Power Network as set out in section 5.4.1 of this access arrangement, converted to an equivalent annualised discount for a defined period of time, as agreed by the parties. Nothing in this calculation prevents the discount exceeding 100% of the equivalent tariff.



7 Adjustments to target revenue in the next access arrangement period

7.1 Adjusting target revenue for unforeseen events

- 7.1.1 If a *force majeure* event occurs which results in Western Power incurring unrecovered costs (within the meaning of the *Code*) during this *access arrangement period* then Western Power will, as part of its *proposed revisions* for the next *access arrangement period*, provide a report to the *Authority* setting out:
 - a) a description of the nature of the *force majeure* event;
 - b) a description of the insurance cover that Western Power had in place at the time of the *force majeure* event; and
 - c) the unrecovered costs borne, or an estimate of the unrecovered costs likely to be borne, by Western Power during thise access arrangement period as a result of the occurrence of the force majeure event-; and
 - a demonstration that the amount to be added to the *target revenue* for the next access arrangement period in respect of those unrecovered costs does not exceed the costs which would have been (or, in the case of estimated costs, would be) borne by a service provider efficiently minimising costs.
- 7.1.2 Pursuant to sections 6.6 to 6.8 of the *Code*, an amount will be added to the *target revenue* for the next *access arrangement period* in respect of the unrecovered costs relating to a *force majeure* event which occurred in this *access arrangement period*.
- 7.1.3 The addition to *target revenue* in the next *access arrangement period* must leave Western Power financially neutral given the timing of when Western Power incurred any unrecovered costs by taking account of:
 - a) the effects of inflation; and
 - b) the time value of money as reflected by Western Power's *weighted average cost* of capital for the Western Power Network as determined in section 5.4.
- 7.1.4 A force majeure event includes but is not limited to any costs arising from the introduction of any scheme or mechanism with respect, directly or indirectly, to emissions of greenhouse gases and with respect to any activity including pricing, reduction, cessation, offset and sequestration (including the Carbon Pricing Mechanism announced by the Commonwealth in February 2011), full retail contestability, and the mandated roll-out of Advanced Interval Meters, contestability, and any other government energy reforms, to the extent that such costs were not included in the calculation of *target revenue* for this access arrangement period or otherwise addressed through the *trigger event* provisions in section 8 of this access arrangement.



EDM 44531823 Page 66

7.2 Adjusting target revenue for technical rule changes

- 7.2.1 If <u>amendments to</u> the *technical rules* <u>are are amendedresult in a material cost</u> <u>impactamended</u> during this *access arrangement period*, Western Power will, as part of its *proposed revisions* for the next *access arrangement period*, provide a report to the *Authority* setting out:
 - a) a description of the nature and timing of the impact of the *technical rule* change on Western Power's *non-capital costs* and *new facilities investment* for this *access arrangement period*; and
 - b) the costs (or cost savings) incurred, or an estimate of the costs (or cost savings) likely to be incurred, by Western Power as a result of that *technical rule* change.
- 7.2.2 Pursuant to sections 6.9 to 6.12 of the *Code*, if the *technical rule* change leads to a cost increase, an amount will be added to the *target revenue* for the next *access arrangement period*.
- 7.2.3 Pursuant to sections 6.9 to 6.12 of the *Code*, if the *technical rule* change leads to a cost saving, an amount will be deducted from the *target revenue* for the next *access arrangement period*.
- 7.2.4 The adjustment to *target revenue* in the next *access arrangement period* must leave Western Power financially neutral given the timing of when Western Power incurred any costs or received cost savings as a result of the *technical rule* change by taking account of:
 - a) the effects of inflation; and
 - b) the time value of money as reflected by Western Power's *weighted average cost* of capital for the Western Power Network- as determined in section 5.4.

7.3 Investment adjustment mechanism

- 7.3.1 In accordance with sections 6.13 to 6.18 of the *Code*, an *investment adjustment mechanism* applies in relation to this *access arrangement*.
- 7.3.2 An amount will be added to, or deducted from, the *target revenue* for the next *access arrangement period* in accordance with the *investment adjustment mechanism* set out below.
- 7.3.3 The *investment adjustment mechanism* will apply separately to each of:
 - a) *new facilities investment* for the *transmission system*; and
 - b) *new facilities investment* for the *distribution system*.
- 7.3.4 The purpose of the *investment adjustment mechanism* is to adjust Western Power's *target revenue* in the next *access arrangement period* in a manner that exactly corrects for the economic loss or gain to Western Power as a result of any *investment difference* in this *access arrangement period* in relation to the categories of *new facilities investment*



specified in section 7.3.7 of this *access arrangement*. In order to give effect to this purpose, the *investment adjustment mechanism* must take account of:

- a) the effects of inflation;
- b) the time value of money as reflected by Western Power's *weighted average cost* of capital for the *Western Power Network* as determined in section 5.4; and
- c) the *capital-related costs* due to any *investment difference* in thise *access arrangement period*.
- 7.3.5 Given the requirements of the *investment adjustment mechanism* as described in section 7.3.4 of this *access arrangement*, Western Power's approach to calculating the *capital-related costs* due to any *investment difference* is to calculate the difference in present value terms between:
 - a) the *target revenue* that would have been calculated for this *access arrangement period* if the *investment difference* had been zero (i.e. there was no forecasting error in relation to the *new facilities investment* categories that are subject to the *investment adjustment mechanism*); and
 - b) the *target revenue* that actually applied in this *access arrangement period*.
- 7.3.6 The amount under section 7.3.2 of this *access arrangement* is equal to the present value of the difference calculated under section 7.3.5 of this *access arrangement*.
- 7.3.7 The categories that are used in calculating the *investment difference* are *new facilities investment*:
 - a) arising from the connection of new generation capacity to the *transmission* system or distribution system from 1 July 20122017;
 - arising from the connection of new *load* to the *transmission system* or distribution system from 1 July 20122017;
 - c) in relation to all *augmentations* to provide additional capacity to the transmission system or distribution system for the provision of covered services from 1 July 2012;
 - d)c) undertaken for *augmentation* of the *distribution system* under the rural power improvement program; 2017;- and
 - e)d) undertaken for *augmentation* of the *distribution system* under the state underground power program.; and
 - f) in relation to<u>arising from the provision of metering installations (within the meaning in the Electricity Industry (Metering Code) 2012) on the distribution system wood pole management for the provision of covered services from from 1 July 20122017.</u>

7.4 Gain sharing mechanism and efficiency and innovation benchmarks

7.4.1 In accordance with sections 5.25 and 6.20 of the *Code*, a *gain sharing mechanism* and *efficiency and innovation benchmarks* will apply with respect to thise access arrangement.



-This gain sharing mechanism applies separately to each of:

<u>the transmission system; and</u>

<u>the distribution system.</u>

7.4.2 Subject to section 7.4.4 of this access arrangement, aAn above-benchmark surplus (within the meaning of the Code) is to be calculated for each of the years 2012/13 to 2016/17transmission system and distribution system for each of the financial years of the access arrangement period ending 30 June 2018 to 30 June 2022 as follows:

 $\frac{ABS_{t1} = EIB_{t1} - A_{t1}}{ABS_{t2} = (EIB_{t2} - A_{t2}) - (EIB_{t1} - A_{t1})}$ $\frac{ABS_{t3} = (EIB_{t3} - A_{t3}) - (EIB_{t2} - A_{t2})}{ABS_{t4} = (EIB_{t4} - A_{t4}) - (EIB_{t3} - A_{t3})}$ $\frac{ABS_{t5} = (EIB_{t5} - A_{t5}) - (EIB_{t4} - A_{t4})}{ABS_{t5} = (EIB_{t5} - A_{t5}) - (EIB_{t4} - A_{t4})}$

 $ABS_{2012/13} = EIB_{2012/13} - A_{2012/13}$ $ABS_{2012/14} = (EIB_{2012/14} - A_{2012/14}) - (EIB_{2012/13} - A_{2012/13})$ $ABS_{2014/15} = (EIB_{2014/15} - A_{2014/15}) - (EIB_{2013/14} - A_{2013/14})$ $ABS_{2015/16} = (EIB_{2015/16} - A_{2015/16}) - (EIB_{2014/15} - A_{2014/15})$ $ABS_{2016/17} = (EIB_{2016/17} - A_{2016/17}) - (EIB_{2015/16} - A_{2015/16})$ $ABS_{2017/18} = EIB_{2017/18} - A_{2017/18}$ $ABS_{2018/19} = (EIB_{2018/19} - A_{2018/19}) - (EIB_{2017/18} - A_{2017/18})$ $ABS_{2019/20} = (EIB_{2019/20} - A_{2019/20}) - (EIB_{2018/19} - A_{2018/19})$ $ABS_{2020/21} = (EIB_{2020/21} - A_{2020/21}) - (EIB_{2019/20} - A_{2019/20})$ $ABS_{2021/22} = (EIB_{2021/22} - A_{2022/21}) - (EIB_{2020/21} - A_{2020/21})$

where:

ABS_t is the above-benchmark surplus in year t of the access arrangement period;

EIB_t is the *efficiency and innovation benchmark* for financial year t as set out in $_{\overline{7}}$ for the *transmission system* and Table 34Table 33 for the *distribution system*, adjusted for:

a) any difference between the actual scale relevant-network growth escalation factors in each financial year and the forecast scalerelevant network growth escalation factors and any difference between the actual relevant-indirect and corporate cost growth escalation factors in each financial year and the forecast relevant-indirect and corporate cost growth escalation factors used to establish the non-capital costs component of approved total costs for each of the transmission system and distribution system for-that financial year, in accordance with section 7.4.9 of thise access arrangement. The scale escalation factors



EDM 44531823 Page 69 are a customer growth rate based on growth in customer numbers and a network growth rate based on increases in line length, increases in substation capacity and increases in the number of distribution transformers; and

b) the effects of inflation;-

Table 7.135: Efficiency and innovation benchmarks for the transmission system (\$M real as at 30 June 20122017)Table 55: Efficiency and innovation benchmarks (\$M real as at 30 June 2017)

Financial year ending:	30 June	30 June	30 June	30 June	30 June
	2013 2018	201 4 <u>2019</u>	2015 2020	2016 2021	2017<u>2022</u>
Transmission networkNetwork	<u>230.152.95</u>	<u>230.452.95</u>	<u>230.8</u> 53.25	<u>231.053.55</u>	<u>230.9</u> 53.55
	<u>3.0</u>	<u>2.6</u>	<u>2.6</u>	<u>2.5</u>	<u>2.2</u>
<u>Corporate</u>	<u>81.229.529</u>	<u>80.621.621</u>	<u>80.121.520</u>	<u>77.121.620</u>	<u>71.821.720</u>
	.2	. 0	. 8	. 8	. 9
Indirect costs	<u>43.210.010</u> <u>.0</u>	<u>39.58.89.1</u>	<u>39.28.88.2</u>	<u>48.711.19. 7</u>	<u>48.211.19. 7</u>
EfficiencyTransmission eEfficiency	<u>354.692.3</u> 4	<u>350.583.3</u> 4	<u>350.1</u> 83.54	<u>356.886.2</u> 4	<u>350.886.4</u> 4
and innovation benchmark - EIBt	44.4 <u>92.2</u>	46 <u>82</u> .6	4 <u>3.081.6</u>	40.6 <u>83.0</u>	52.0 <u>82.8</u>



Financial year ending:	30 June 2018	30 June <u>2019</u>	30 June <u>2020</u>	30 June <u>2021</u>	30 June <u>2022</u>
Distribution network	177.0177.8	178.3178.8	179.9179.9	181.4181.1	182.8182.3
<u>Corporate</u>	<u>80.779.9</u>	59.157.4	58.956.9	59.257.0	59.557.2
Indirect costs	<u> 30.130.2</u>	26.827.9	26.825.4	<u>33.930.3</u>	34.4<u>30.6</u>
Distribution efficiency and innovation benchmark—EIB,	287.7287.9	264.2264.1	265.6262.3	274.5268.4	276.6270.1

Table 36: Efficiency and innovation benchmarks for the distribution system (\$M real as at 30 June 2017)

and

At is the sum of the sum of the actual non-capital costs incurred by Western Power for each of the transmission system and distribution system in year t, excluding any amount of non-capital costs incurred by Western Power-relevant to the transmission system and distribution system:

- i. in accordance with the D-factor scheme in thise access arrangement and providing that the expenditure has been approved by the Authority.
- ii. in accordance with any adjustment made under section 7.1 of this access arrangement:
- iii. in accordance with any adjustment made under section 7.2-of this access arrangement:
- iv. in relation to superannuation for defined benefits schemes;
- v. in relation to *non-revenue captarget* services;
- vi. in relation to licence fees;
- vii. in relation to <u>a levy made under section 14 of the Energy Safety Act 2006</u> (WA) applicable to Western Powerthe <u>energy safetyEnergySafety</u> levy; and
- viii. in relation to network control services
- ix.viii. in relation to amounts payable under the *Economic Regulation Authority* (*Electricity Network Access Funding Regulations*) 2012.

7.4.3 The gain sharing mechanism amount (GSMA_{AA}) for the *access arrangement period* is to be calculated as follows:

 $\underline{\text{GSMA}}_{AA} = \sum [\underline{\text{GSMA}}_{1:5}]$

<u>where:</u>

 $\underline{\mathsf{GSMA}_1} = \max\left(0, \underline{\mathsf{ABS}_{t1}} + \underline{\mathsf{ABS}_{t2}} + \underline{\mathsf{ABS}_{t3}} + \underline{\mathsf{ABS}_{t4}} + \underline{\mathsf{ABS}_{t5}}\right)$

 $\underline{\mathsf{GSMA}}_2 = \max\left(\mathbf{0}, \underline{\mathsf{ABS}}_{t2} + \underline{\mathsf{ABS}}_{t3} + \underline{\mathsf{ABS}}_{t4} + \underline{\mathsf{ABS}}_{t5}\right)$

 $\underline{\mathsf{GSMA}}_3 = \max(\mathbf{0}, \mathsf{ABS}_{t3} + \mathsf{ABS}_{t4} + \mathsf{ABS}_{t5})$

 $\underline{\mathsf{GSMA}_4} = \max\left(0, \underline{\mathsf{ABS}_{t4}} + \underline{\mathsf{ABS}_{t5}}\right)$



$\underline{\text{GSMA}_5} = \max(0, ABS_{t5})$

where:

GSMA_n is the total *above-benchmark surplus* for the equivalent year of the *access arrangement period*; and

<u>ABS_t is the *above-benchmark surplus* in year t of the *access arrangement period* calculated in accordance with section 7.4.2.</u>

- 7.4.4 In any year in which <u>for the transmission system</u> an above-benchmark surplus is calculated to be a positive value <u>under section</u> 7.4.2:
 - a) where Western Power failed to provide *reference services* at a *service standard* at least equivalent to the *service standard benchmarks* for those *reference services* for that year as set out in section 4 of the access <u>arrangement:</u>
 - <u>after notification from Western Power under section</u> 7.4.6, <u>a</u>
 <u>determination will be made by the Authority of the extent (expressed as</u>
 <u>a percentage) that Western Power achieved the above-benchmark</u>
 <u>surplus by failing to provide reference services at a service standard at</u>
 <u>least equivalent to the service standard benchmarks for those reference</u>
 <u>services for that year as set out in section 4; and</u>
 - ii. the percentage determined by the Authority in 7.4.4(a)(i) will be applied as a proportion of the year (the "SSB Deficiency Proportion") in accordance with section 7.4.7; and
 - b) where Western Power provided *reference services* at a *service standard* at least equivalent to the *service standard benchmarks* for those *reference services* for that year as set out in section 4, there is no SSB Deficiency *Proportion*.
- 7.4.5 In any year in which an *above-benchmark surplus* is calculated to be a negative value under section 7.4.2 there is no SSB Deficiency Proportion.
- 7.4.37.4.6 For the purposes of section 7.4.4(a), <u>Hi</u>f in any year in which an *above-benchmark* surplus is calculated to be a positive value for the transmission system or the distribution system and Western Power fails to provide a relevant reference services at a service standard at least equivalent to the relevant service standard benchmarks, for those reference services for that year as set out in section 4 of the access arrangement, Western Power will demonstrate to may notify the Authority and demonstrate to it how and to what extent there is, or is not, a relationship between that failure and Western Power's achieved above-benchmark surplus relevant efficiency gains or innovation in excess of the efficiency and innovation benchmarks, through consideration of:
 - a) which *service standard benchmarks* has ve not been met in that year;
 - b) an analysis of the causes for not meeting the *service standard benchmark* in that year;



EDM 44531823 Page 72
- c) the categories of *non-capital costs* that impact on the achievement of th<u>oseat</u> service standard benchmarks (which may be sub-categories of the cost categories in section 7.4.27.4.811);
- d) after normalising the forecast non-capital costs for those categories in section 7.4.6(c)_ used to establish the non-capital costs component of approved total costs, after normalising for inflation (using the CPI), and scalenetwork growth escalation factors and indirect and corporate cost growth escalation factors in a manner that is consistent with 7.4.8, whether there has, or has not, been an underspend in those non-capital costs categories; or and
- e) any other issues that are relevant.

-This information will be used to determine the extent, if any, that Western Power achieved <u>relevant</u> efficiency gains or innovation in excess of the *efficiency and innovation benchmarks* during this access arrangement period by failing to provide <u>relevant</u> reference services at a service standard at least equivalent to the <u>relevant</u> service standard benchmarks.

 7.4.7
 Subject to section 7.4.8 of this access arrangementA total gain sharing mechanism

 revenue amount for the access arrangement (GSMR), the following amounts GSMAt will be added to target revenue for the next access arrangement period calculated as follows:each of the transmission system and the distribution system for one or more access arrangement periods covering the financial years 2017ending 30 June 2023 to 30 June 2027:

 $\underline{\text{GSMR} = \text{GSMA}_{AA} - (\text{GSMA}_{AA} \times (\Sigma \text{SSB Deficiency Proportion /AA Length}))}$

where:

GSMA_{AA} is the total *above-benchmark surplus* for the *access arrangement period* calculated in accordance with section 7.4.3;

SSB Deficiency Proportion is determined under section 7.4.4(a)ii); and

AA Length is the number of years in the access arrangement period.

7.4.4 <u>GSMA_{2022/23} = ABS_{2017/18} to 2021/22</u>:

GSMA_{2017/18} = ABS_{2012/13} + ABS_{2013/14} + ABS_{2014/15} + ABS_{2015/16} + ABS_{2016/17}

GSMA₂₀₁₈+ ABS_{2018/19} = ABS_{2013/14} + ABS_{2014/15} + ABS_{2015/16} + ABS_{2016/17}

GSMA₂₀₁₉+ABS_{2019/20} = ABS_{2014/15} + ABS_{2015/16} + ABS_{2016/17}

GSMA₂₀₂₀+ ABS_{2020/21} = ABS_{2015/16} + ABS_{2016/17}+ ABS_{2021/22}

GSMA_{2021/22} = ABS_{2016/17}

<u>GSMA_{2023/24} = ABS_{2018/19} + ABS_{2019/20} + ABS_{2020/21} + ABS_{2021/22}</u>



$-\underline{\mathsf{GSMA}_{2024/25}} = \underline{\mathsf{ABS}_{2019/20}} + \underline{\mathsf{ABS}_{2020/21}} + \underline{\mathsf{ABS}_{2021/22}}$

<u>GSMA_{2025/26} = ABS_{2020/21} + ABS_{2021/22}</u>

<u>GSMA_{2026/27} = ABS_{2021/22}</u>

where:

GSMA_t is the gain sharing mechanism adjustment to target revenue for <u>each of the</u> transmission system and the distribution system for year t.

7.4.5 In any year where the amount of an adjustment to *target revenue* for the transmission <u>system or the distribution system</u> determined under section 7.4.7 of this access arrangement is a negative value, the amount of the adjustment to *target revenue* for the transmission system or the distribution system respectively in that year is zero.

7.4.67.4.8 The gain sharing mechanism does not affect the ordinary operation of the transmission system and distribution system revenue capstargets (absent the gain sharing mechanism), which already provides for Western Power to retain 100% of any efficiency gains achieved during thise access arrangement period. This characteristic is consistent with section 6.24 of the Code which ensures that Western Power can retain all of the surplus achieved in thise access arrangement period.

 7.4.77.4.9
 The adjustment to EIBt due to any differences between the actual scalerelevant

 network growth
 escalation factors in each financial year and the forecast scalerelevant

 network growth
 escalation factors and any differences between the actual relevant

 indirect and corporate-cost growth
 escalation factors in each financial year and the

 forecast
 relevant-indirect and corporate-cost growth

 escalation
 factors used to establish

 the non-capital costs
 component of approved total costs

 system and distribution system for
 that financial year will be calculated by:

- a) deflating EIB_t for financial year t by using:
 - the scalethe network growth escalation factors and indirect and corporate cost growth escalation factors assumed for financial year t when setting the forecast non-capital cost component of approved total costs for each of the transmission system and distribution system for that financial year, compounded to that financial year, as set out in Table 56, Table 57 and Table 58; and
 - ii.— the applicable scale escalation factor for financial year t determined for each category of expenditure as set out in Table 35; and
- b) inflating the value determined under section 7.4.9(a) for financial year t using:
 - the scalenetwork growth escalation factors recalculated for financial year t using actual data for each scale escalation driver<u>of the transmission</u> system and distribution system for each relevant-network growth escalation factor in each financial year, compounded to that financial



year, and following the calculation method set out in <u>Table</u> 56, and <u>Table</u> 57; and

ii. <u>the applicable scale</u>indirect and corporate cost growth escalation factor_factors recalculated for financial year t determined using actual data_for each category of the *transmission system* and *distribution system*, compounded to that financial year, following the calculation method set out in Table 58 and section 7.4.107.4.117.4.11.

—When inflating the EIB value determined under section-7.4.10a) 7.4.9(a) 7.4.10(a) for indirect and corporate cost growth escalation factors:

- a) The growth factor applied to corporate costs is a weighted average of the *distribution* system and transmission system recalculated network growth escalation factors. The weighting is based on the total corporate operating expenditure allocated to the *distribution system* (as set out in Table 35.a proportion of total corporate operating expenditure) and the total corporate operating expenditure allocated to the *transmission* system (as a proportion of total corporate operating expenditure) in accordance with the <u>Cost and Revenue Allocation Methodology and derived from the Regulatory Financial</u> <u>Statements for financial year t.</u>
- 7.4.10 , Tthe growth factor applied to indirect costs is a weighted average of the *distribution* system and transmission system recalculated network growth escalation factors. The weighting is based on the total *distribution system* operating expenditure that attracts indirect costs (as a proportion of total operating expenditure that attracts indirect costs) and the total *transmission system* operating expenditure that attracts indirect costs (as a proportion of total operating expenditure that attracts indirect costs (as a proportion of total operating expenditure that attracts indirect costs); in accordance with the Cost and Revenue Allocation Methodology and derived from the Regulatory Financial Statements for financial year t.

Table 7.237: Distribution system forecast network growth escalation assumptions

Table 34: Forecast scale escalation assumptionsScale escalation driverNetwork growth factor	Calculation method	2011/12 <u>Weight</u>	2012/13 2017/18	2012/14 2018/19	2014/15 2019/20	2015/16 2020/21	2016/17 2021/22
Customer numbers f actor	Year on year growth	2.41%	2.41%	2.41%	2.41%	2.41%	2.41%
Total line length <u>Customer</u> numbers (a)	Year on year growth	<u>45.8%1. 31<u>67.6</u>%</u>	1. 31<u>65</u>%	1. 31<u>73</u>%	1. 31<u>69</u>%	1. 31<u>66</u>%	1. 31<u>63</u>%
Distribution transformers <u>Circuit</u> length (b)	Year on year growth	<u>23.8%1. 33<u>10.7</u>%</u>	1.33 0.9 <u>1</u> %				

Table 56: Distribution system forecast network growth escalation assumptions



Table 34: Forecast scale escalation assumptionsScale escalation driverNetwork growth factor	Calculation method	2011/12 Weight	2012/13 2017/18	2012/14 2018/19	2014/15 2019/20	2015/16 2020/21	2016/17 2021/22
Zone substation capacityRatcheted Maximum Demand (c)	Year on year growth	<u>17.6%</u> 3. 65 <u>21.7</u> %	3.65<u>0.0</u> <u>0</u>%	3.65<u>0.0</u> <u>0</u>%	3.65<u>0.0</u> 0%	3.65<u>0.0</u> <u>0</u>%	3.65<u>0.0</u> <u>0</u>%
Energy delivered (d)	<u>Year on year</u> growth	<u>12.8%</u>	<u>-0.37%</u>	<u>-0.20%</u>	<u>-0.20%</u>	<u>-0.71%</u>	<u>-1.10%</u>
<u>Customer and</u> Network growth factor	AverageWeight ed average of a, b-and, -c and d	<mark>2.10</mark> 100 %	<u>0.92%2. 101.21</u> %	<u>0.98%2. 10<u>1.26</u> %</u>	<u>0.97%2. 101.24</u> %	<u>0.89%2. 101.22</u> %	<u>0.82%2. 101.20</u> %

Table 7.338: Scale<u>Transmission system forecast network growth</u> escalation factor for each category of expenditure<u>assumptions</u>

Network growth factor	Calculation method	Weight	2017/18	2018/19	2019/20	2020/21	2021/22
Circuit length (a)	Year on year growth	<u>37.6%</u> 28 .7%	0.32%	0.33%	0.22%	0.33%	0.32%
Ratcheted Maximum Demand (b)	Year on year growth	<u>19.4%22 .1%</u>	0.00%	0.00%	0.00%	0.00%	0.00%
Energy Delivered (c)	Year on year growth	<u>23.1%21 .4%</u>	_ <u>0.37%</u> 0. 30%	_ <u>0.20%</u> 0. 00%	_ <u>0.20%</u> 2. 89%	_ <u>0.71%</u> 2. 50%	_ <u>1.10%0. 00%</u>
Weighted entry and exit connection pointsCustomer numbers (d)	Year on year growth	<u>19.9%27 .8%</u>	<u>0.00%-</u> 0.24%	<u>0.00%-</u> 0.73%	<u>2.63%-</u> 0.25%	<u>2.56%-</u> 0.98%	<u>0.00%</u> 0. 00%
Network growth factor	Weighted average of a, b, c and d	100%	<u>0.03%</u> 0. 09%	<u>0.08%</u> - 0.11%	<u>0.56%</u> 0. 62%	<u>0.47%0. 35%</u>	_ <u>0.13%</u> 0. 09%

Table 57: Transmission system forecast network growth escalation assumptions

Table 7.439: Indirect and corporate cost forecast growth escalation assumptions

Table 58: Indirect cost forecast growth escalation assumptions

<u>Growth escalation</u> <u>factor</u>	<u>Calculation</u> <u>method</u>	<u>2017/18</u>	<u>2018/19</u>	<u>2019/20</u>	<u>2020/21</u>	<u>2021/22</u>
Indirect	<u>Year on year</u>	0.700%0.9	0.7 <u>66%0.9</u>	0.87% 1.09	0.7 <u>8</u> 8% <u>1.0</u>	0. <u>5959%0.</u>
	growth	<u>3%</u>	<u>2%</u>	<u>%</u>	<u>1%</u>	<u>92%</u>
<u>Corporate</u>	Year on year	0.69%0.91	<u>0.74%0.90</u>	0.86%1.08	<u>0.78%0.99</u>	0.57%0.91
	growth	<u>%</u>	<u>%</u>	<u>%</u>	<u>%</u>	<u>%</u>



7.4.87.4.11 For the purposes of clausesection 7.4.9(a)(i(i) the actual data used for each scalerelevant network growth escalation driverfactor must be independently audited. The audit must be carried out by an independent auditor approved by the Authority, with Western Power managing and funding the audit. -The scope of the audit will be determined by the Authority.

7.4.9—

7.5 Service standards adjustment mechanism

- 7.5.1 In accordance with section 6.30 of the *Code*, a *service standards adjustment mechanism* applies in relation to the financial year ending 30 June 2019 and following financial years ending 30 June of thise access arrangement ("SSAM Year").
- 7.5.2 An amount will be added to, or deducted from, the *target revenue* for each of the *transmission system* and the *distribution system* for the next *access arrangement period* in accordance with the *service standards adjustment mechanism* set out below.
- 7.5.3 The service standards adjustment mechanism will apply to the **"SSAM SSBs"** meaning the service standard benchmarks for SAIDI, SAIFI, call centre performance, circuit availability, system minutes interrupted radial, loss of supply event frequency and average outage duration as defined in section 4-of this access arrangement.
- 7.5.4 In relation to actual service performance for each <u>of the financial years ending 30 June</u> <u>2018 and 30 June 2019, and the following financial years ending 30 June ("SST Year")year</u> <u>of this access arrangement periodSSAM year</u> for each SSAM SSB a reward (a positive amount) or penalty (a negative amount) will be calculated <u>for each SSAM SSB</u> by applying the applicable incentive rate to the relevant Service Standard Difference ("SSD"). The SSD is calculated as follows:
 - a) if SSA_t < SSB for SAIDI, SAIFI, system minutes interrupted radial, loss of supply event frequency and average outage duration; or

SSA_t > SSB for call centre performance and circuit availability then

 $SSD_t = (SST - SSA_t)$

b) if SSA_t \geq SSB for SAIDI, SAIFI, system minutes interrupted – radial, loss of supply event frequency and average outage duration; or

 $SSA_t \leq SSB$ for call centre performance and circuit availability then

 $SSD_t = (SST - SSB)$

where:

SSD_t is the service standard difference in <u>SSAM ySST Y</u>ear t;

SST is the SSAM target detailed in section 7.5.11 of this access arrangement;



SSB is the *service standard benchmark* for the *SSAM SSBs* as defined in section 7.5.3 of this *access arrangement*; and

SSA_t is the actual service performance in <u>SST YSSAM</u> year t with respect to the SSAM SSBs.

- 7.5.5 In relation to SAIDI and SAIFI, the rewards or penalties are calculated as the sum of the application of the formulae in section 7.5.4-of this *access arrangement* to each component of SAIDI and SAIFI.
- 7.5.6 The rewards and penalties are applied to the performance <u>SST YSSAM y</u>ear in thise access arrangement period and:
 - a) the reward or penalty for circuit availability will be allocated to the performance of the *transmission system*;
 - b) the reward or penalty for SAIDI and SAIFI will be allocated to the performance of the *distribution system*;
 - c) the reward or penalty for call centre performance will be allocated to the performance of the *distribution system*;
 - d) the reward or penalty for system minutes interrupted radial will be allocated to the performance of the *transmission system*;
 - e)d) the reward or penalty for loss of supply event frequency will be allocated to the performance of the *transmission system*; and
 - f)e) the reward or penalty for average outage duration will be allocated to the performance of the *transmission system*.
- 7.5.7 The rewards and penalties applied to each <u>SST YSSAM y</u>ear as allocated to each of the *transmission system* and *distribution system* are summed for each of the *transmission system* and *distribution system*.
- 7.5.8 Notwithstanding section 7.5.7 of this access arrangement, the sum of the rewards or penalties for the transmission system applied to each <u>SSAM-ySST Y</u>ear is capped at 1% of TR_t for that year as definedset out in <u>Table [27]</u>. Table 50Error! Reference source not found... For the avoidance of doubt, for the purposes of this section <u>5.6.6. TR_t in that table will not be updated as a result of the annual updates to weighted average costs of capital as determined in section 5.4.</u>
- 7.5.9 Notwithstanding section 7.5.7 of this access arrangement, the sum of the rewards or penalties for the distribution system applied to each <u>SST YSSAM year</u> is capped at 51% of DRt for that year, and the sum of the penalties for the distribution system applied to each <u>SST Year</u> is capped at 2.5% as definedset out in Table 51-Table [28]. For the avoidance of doubt, for the purposes of this section 5.7.6. DRt in that table will not be updated as a result of the annual updates to weighted average costs of capital as determined in section 5.4.



7.5.10 The amount that will be added to, or deducted from, the *target revenue* for each of the *transmission system* and the *distribution system* is equal to the present value of the sum of the amounts for each of the *transmission system* and the *distribution system* calculated under section 7.5.7 of this *access arrangement* (as subject to sections 7.5.8 and 7.5.9 of this *access arrangement*).

7.5.11 The SSAM targets and incentive rates for the *SSAM SSBs* are as follows:

 Table 7.540: SAIDI SSAM targets (for year ending 30 June) and incentive rates (\$ real as at 30 June 20122017)

 Table 59: SAIDI SSAM targets and incentive rates (\$ real as at 30 June 2017)

	SSAM target (SSTt) for years ending 30 June 2018 and 30 June 20198	SSAM target (SSTt <u>) for each</u> SSAM-ySST Year	Reward side incentive rate (\$ per SAIDI minute)	Penalty side incentive rate (\$ per SAIDI minute)
SAIDI - CBD (minutes)	Ξ	<u>17.720.317.8</u>	<u>30,216</u> 67,817 <u>26,734</u>	<u>30,216</u> 67,817 <u>26,734</u>
SAIDI - Urban (minutes)	Ξ	<u>106.8</u> 136.6 <u>108.7</u>	<u>446,672</u> 529,816<u>366,800</u>	<u>446,672</u> 529,816<u>366,800</u>
SAIDI - Rural Short (minutes)	Ξ	<u>188.6</u> 207.8 <u>190.4</u>	<u>143,122</u> 223,472 <u>114,374</u>	<u>143,122</u> 223,472 <u>114,374</u>
SAIDI - Rural Long (minutes)	=	<u>677.7</u> 582.2 <u>675.6</u>	<u>52,504</u> 65,219 <u>41,958</u>	<u>52,504</u> 65,219 <u>41,958</u>

Table 7.641: SAIFI SSAM targets (for year ending 30 June) and incentive rates (\$ real as at 30 June 20122017)

Table 60: SAIFI SSAM targets and incentive rates (\$ real as at 30 June 2017)

	SSAM target (SST _t) for years ending 30 June 2018 and 30 June 20198	SSAM target (SST _t) <u>for each</u> SSAM-ySST Year	Reward side incentive rate (\$ per 0.01 event)	Penalty side incentive rate (\$ per 0.01 event)
SAIFI - CBD (events)	Ξ	<u>0.12</u> 0.14	<u>29,225</u> 87,081 <u>30,114</u>	<u>29,225</u> 87,081 <u>30,114</u>
SAIFI - Urban (events)	=	<u>1.09</u> 1.36 <u>12</u>	<u>290,705</u> 548,988 <u>366,867</u>	<u>290,705</u> 548,988 <u>366,867</u>
SAIFI - Rural Short (events)	=	<u>1.96<mark>2.2701</mark></u>	<u>91,822222,511<u>117,788</u></u>	<u>91,822222,511<u>117,788</u></u>
SAIFI - Rural Long (events)	=	<u>4.29</u> 4.06 <u>67</u>	<u>55,342</u> 101,725 <u>65,982</u>	<u>55,342</u> 101,725 <u>65,982</u>



Table 7.742: Call centre performance SSAM target (for year ending 30 June) and incentive rate (\$ real as at 30 June 20122017)

Table of Carterine pe								
	SSAM target (SST _t) for years ending <u>30 June 2018 and</u> <u>30 June 20198</u>	SSAM target (SST _t) for each <u>SSAM</u> <u>SST Year</u>	Reward side incentive rate (\$ per 0.1%)	Penalty side incentive rate (per 0.1%)				
Call centre performance (Percentage of calls responded to within 30 seconds)	Ξ	<u>92.0%</u> 87.6 <u>92.2</u> %	<u>-38,017 -41,140 - 43<u>43,042</u></u>	<u>-12,429 -9,540 41,084<u>99,807</u></u>				

Table 61: Call centre performance SSAM target and incentive rate (\$ real as at 30 June 2017)

Table 7.843: Circuit availability SSAM target (for year ending 30 June) and incentive rate (\$ real as at 30 June 20122017)

Table 62: Circuit availability SSAM target and incentive rate (\$ real as at 30 June 2017)

	SSAM target (SST _t) for years ending 30 June 2018 and 30 June 20198	SSAM target (SST _t) for each <u>SSAM</u> <u>SST Year</u>	Reward side incentive rate (\$ per 0.1%)	Penalty side incentive rate (\$ per 0.1%)
Circuit availability (Percentage of total possible hours available)	Ξ	<u>98.5%</u> 98.1 <u>5</u> %	<u>-449,344 -434,953- 421<u>421,856</u></u>	<u>-256,768-193,313- 187<u>187,492</u></u>

Table 7.944: System minutes interrupted - Radial: Loss of supply event frequency SSAM target (for year ending 30 June) and incentive rate (\$ real as at 30 June 20122017)

Table 63: Loss of supply event frequency SSAM target and incentive rate (\$ real as at 30 June 2017)

-	SSAM target (SST _t) for years ending 30 June 2018 and 30 June 20198	SSAM target (SST _t) <u>for each</u> <u>SSAM year</u>	Reward side incentive rate (\$ per minute)-<u>event)</u>	Penalty side incentive rate (\$ per minute<u>event</u>)
SystemLoss of supply event frequency >0.1 and ≤1.0 system minutes interrupted - Radial (minutes(number) of events)	1.9_	<u>17105,44317</u>	<u>89,86943,495</u> 172,039 <u>42,186</u>	<u>59,91254,369</u> <u>52,732</u>



(\$

-	SSAM target (SST _t) for years ending 30 June 2018 and 30 June 20198	SSAM target (SST _t <u>) for each</u> <u>SSAM year</u>	Reward side incentive rate (\$ per minute)-<u>event)</u>	Penalty side incentive rate (\$ per minute<u>event</u>)
Loss of supply event frequency >1.0 system minutes interrupted (number of events)	Ξ	<u>312</u>	<u>179,737108,738 140,619</u>	<u>134,803217,477 421,856</u>

Table 7.1045: Loss of supply event frequency: Average outage duration30 June) and incentive rate (\$ real as at 30 June 20122017)

-	SSAM target (SSTt) for years ending 30 June 2018 and 30 June 20198	SSAM target (SST _t) <u>for each</u> SSAM-ySST Year	Reward side incentive rate (\$ per event)<u>minute)</u>	Penalty side incentive rate (\$ per event<u>minute</u>)
Loss of supply event frequency >0.1 system minutes interrupted (number of events)		24	36,319	27,240
Loss of supply event frequency >1.0 system minutes interrupted (number of events)Average outage duration (minutes)	Ξ	<u>7082871</u>	<u>14,0971,8831<u>1,826</u></u>	<u>1,3673,000163,437<u>2,909</u></u>

Table 64: Average outage duration SSAM target and incentive rate (\$ real as at 30 June 2017)

Table 42: Average outage duration SSAM target (for year ending 30 June) and incentive rate (\$ real as at 30 June 2012)

-	SSAM target (SST _t)	Reward side incentive rate (\$ per minute)	Penalty side incentive rate (\$ per minute)
Average outage duration (minutes)	698	3,477	2,495



7.6 D factor

- 7.6.1 In <u>clausesection</u> 7.6.3 "**network control service**" means demand-side management or generation solutions (such as *distributed generating plant*) that can be a substitute for *network augmentation*.
- 7.6.2 This D factor scheme applies separately to each of:
 - a) non-capital costs for the transmission system; and
 - b) *non-capital costs* for the *distribution system*.
- 7.6.3 In the next *access arrangement period*, the *Authority* will add to Western Power's *target revenue* an amount so that Western Power is financially neutral as a result of:
 - a) any additional *non-capital costs* incurred by Western Power as a result of deferring a *new facilities investment* project during this *access arrangement period*, net of any amounts previously included in *target revenue* in relation to the deferred *new facilities investment* (other than such amounts included in the calculation of the *capital-related costs* due to any *investment difference* under clausesection 7.3.5); and
 - b) any additional *non-capital costs* incurred by Western Power in relation to demand management initiatives or *network control services*.

<u>("D factor incurred costs").</u>

- 7.6.4 In relation to <u>section</u> 7.6.3(a), the *new facilities investment* project that has been deferred must have been included in the *forecast new facilities investment* for this *access arrangement period*.
- 7.6.5 In relation to <u>sections</u> 7.6.3(a) and 7.6.3(b), an amount will only be added to *target revenue* for the next *access arrangement period* if there is an approved business case for the relevant expenditure, and this business case is made available to the *Authority*. The business case must demonstrate to the *Authority's* satisfaction that the proposed *non-capital costs* satisfy the requirements of sections 6.40 and 6.41 of the *Code*, as relevant. (<u>"D factor non-capital costs test"</u>).

Western Power may at any time during this access arrangement period apply to the Authority for the Authority to determine that a business case contains proposed noncapital costs that satisfy the D factor non-capital costs test.

If an application is made to the Authority under section 7.6.6 the Authority must make a determination within 25 Business Days, unless the Authority forms the view that public consultation should be undertaken, in which case the timeframe will be adjusted in accordance with the timeframes described in Appendix 7 of the Code, but shall be no longer than 45 business days...



If the Authority determines that proposed non-capital costs satisfy the D factor noncapital costs test ("approved business case amount") then if D factor incurred costs are not more than the approved business case amount the Authority will add the D factor incurred costs to Western Power's target revenue in the next access arrangement period. If the D factor incurred costs are more than the approved business case amount, the Authority will add the D factor incurred costs to Western Power's target revenue in the next access arrangement period and Western Power may seek the further amount be added to target revenue for the next access arrangement period by demonstrating to the Authority's satisfaction that the further amount of non-capital costs satisfy the requirements of sections 6.40 and 6.41 of the Code.

<u>A determination of an *approved business case amount* does not oblige Western Power to proceed with the project that is the subject of the business case.</u>

If the Authority determines that proposed non-capital costs do not satisfy the D factor non-capital costs test then the Authority will provide reasons for that determination to Western Power and Western Power may make an amended application under section 7.6.67.6.6.

- 7.6.6 In relation to <u>sections</u> 7.6.3(a) and 7.6.3(b), the adjustment to the *target revenue* for the next *access arrangement period* must leave Western Power financially neutral by taking account of:
 - a) the effects of inflation; and
 - b) the time value of money as reflected by Western Power's *weighted average cost* of capital for the *Western Power Network* as determined in section 5.4.

7.7 Deferred Initial d Deferred revenue

- 7.7.1 For the purposes of <u>clausessections</u> 6.5A to 6.5E of the *Code* an amount must be added to the target revenue for the *distribution system* in the <u>fourthfifth access arrangement</u> <u>period or subsequent access arrangement periods such that the present value (at 30 June 2017) of the total amount added to target revenue (taking account of inflation and the time value of money) is equal to \$408.8 million (\$ real as at 30 June 2017).</u>
- 7.7.1 For the purposes of sections 6.5A to 6.5E of the Code an amount must be added to the target revenue for the transmission system in the fifth access arrangement period or subsequent access arrangement periods such that the present value (at 30 June 20122017) of the total amount added to target revenue (taking account of inflation and the time value of money) is equal to \$520.589.0 million (\$ real as at 30 June 2012).
- 7.7.2 For the purposes of clauses 6.5A to 6.5E of the *Code* an amount must be added to the target revenue for the *transmission system* in the fourth *access arrangement period* or subsequent *access arrangement periods* such that the present value (at 30 June 2012) of the total amount added to *target revenue* (taking account of inflation and the time value of money) is equal to \$70.5 million (\$ real as at 30 June 2012<u>2017</u>).



7.7.3 The timeframe for recovering the deferred revenue amounts in section 7.7.1 will be $\frac{3732}{3732}$ years and in section 7.7.2 $\frac{1.1.1}{1.1}$ will be $\frac{4540}{3732}$ years.



8 Trigger events

- 8.1.1 Pursuant to section 4.37 of the *Code* a *trigger event* is any significant unforeseen event which has a materially adverse financial-impact on Western Power and which is:
 - a) outside the control of Western Power; and
 - b) not something that Western Power, acting in accordance with *good electricity industry practice*, should have been able to prevent or overcome; and
 - c) so substantial that the advantages of making a variation to this *access arrangement* before the end of this *access arrangement period* outweigh the disadvantages, having regard to the impact of the variation on regulatory certainty.
- 8.1.2 A trigger event may include without limitation the introduction of any scheme or mechanism with respect, directly or indirectly, to emissions of greenhouse gases and with respect to any activity including pricing, reduction, cessation, offset and sequestration (including the Carbon Pricing Mechanism announced by the Commonwealth in February 2011), full retail contestability, and the mandated roll-out of Advanced Interval Meters, contestability, and any other government energy reforms, to the extent that such costs were not included in the calculation of *target revenue* for this access arrangement period or otherwise addressed through the unforeseen event provisions in sections 7.1.1 to 7.1.4 of this access arrangement.
- 8.1.38.1.2 The designated date by which Western Power must submit proposed revisions to the Authority is 90 business days after a trigger event has occurred. If the costs associated with the trigger event are uncertain at the time of the designated date, Western Power's proposed revision to the Authority under section 4.37 of the Code must incorporate an appropriate mechanism for cost recovery having regard to the Code objective.



9 Supplementary matters

9.1 they Balancing

9.1 Balancing requirements under General

- <u>Previous versions of</u> the access arrangement shall be in accordance with <u>have referred, in</u> the Supplementary Matters chapter, to balancing requirements, ancillary service, trading and settlement requirements.
- <u>Under the Wholesale Electricity Market Rules these functions are now principally</u> undertaken by the Australian Energy Market Operator ("AEMO").
- 9.1.1 However-Western Power will discharge such the obligations it has under in relation to these matters as they are imposed upon Western Power by the Wholesale Electricity Market Rules ("WEM Rules") as in force from time to time relating to balancing requirements, ancillary services, trading and settlement requirements and, in accordance with the WEM those rRules. Western Power will also support the Australian Energy Market Operator ("AEMO") in the discharge of its functions, including by providing information to AEMO as required by the Wholesale Electricity Market WEM Rules. As at 2 October 2017 this access arrangement is prepared by Western Power, the principal role Western Power will have is to provide network information to AEMO to support settlements and balancing.

{Note: Previous versions of the access arrangement have referred, in the Supplementary Matters chapter, to balancing requirements, ancillary service, trading and settlement requirements. Under the WEM Rules, these functions are now principally undertaken by AEMO. This occurred when the System Management functions were transferred from Western Power to AEMO on 1 July 2016. As at 1 July 2016, Western Power's principal role in respect to these functions under the WEM Rules is to provide network information to AEMO to support settlements and balancing.}

9.2 Line losses

9.2.1 Requirements for the treatment of line losses under the *access arrangement* shall be in accordance with the Wholesale Electricity Market Rules.

9.3 Metering

9.3.1 Metering requirements under the *access arrangement* shall be in accordance with the *Electricity Industry (Metering Code-2005) 2012* and the Metering Code Model Service Level Agreement.

9.4 Ancillary services



9.4.19.3.1 Requirements for model service level agreement most recently approved by the treatment of ancillary services <u>Authority</u> under the *access arrangement* shall be in accordance with the Wholesale Electricity Market Rules.<u>Industry (Metering Code)</u> 2012MSLA.

9.5 Stand-by

9.5.1 Under the Wholesale Electricity Market Rules there is no requirement for stand-by generation.

9.6 Trading

9.6.1 Trading requirements under the *access arrangement* shall be in accordance with the Wholesale Electricity Market Rules.

9.7 Settlement

9.7.1 Settlement requirements under the *access arrangement* shall be in accordance with the Wholesale Electricity Market Rules.



APPENDICES



Appendix A. Electricity transfer access contract



Appendix B. Applications and queuing policy



Appendix C. Contributions policy

- C.1 Contributions policy
- C.2 Distribution headworks methodology

C.3C.2 Distribution low voltage connection headworks scheme methodology



Appendix D. Transfer and relocation policy



Appendix E. Reference services



Appendix F. Reference tariffs

- F.1 2012/132017/18 price list
- F.2 2012/132017/18 price list information
- **F.3** 2018/19 price list
- F.4 2018/19 price list information
- F.5 2019/20 price list
- F.6 2019/20 price list information

